

Control Commands

Model No. PT-RZ870
PT-FRZ88C



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RZ870 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C		
BASIC OPERATION REMOTE CONTROL	POWER	ON		PON	QPW	001		✓	
		OFF (STANDBY)		POF		000		✓	
	INPUT SELECT	COMPUTER1		IIS: RG1		QIN	RG1		✓
		COMPUTER2		IIS: RG2			RG2		✓
		VIDEO		IIS: VID			VID		✓
		Y/C		IIS: SVD			SVD		✓
		DVI		IIS: DVI			DVI		✓
		HDMI1		IIS: HD1			HD1		✓
		SDI1		IIS: SD1			SD1		✓
		DIGITAL LINK		IIS: DL1			DL1		✓
	INPUT SELECT (DIGITAL LINK)	COMPUTER1		IIS: DL1: PC1		QIN	DL1: PC1		✓
		COMPUTER2		IIS: DL1: PC2			DL1: PC2		✓
		VIDEO		IIS: DL1: VID			DL1: VID		✓
		HDMI1		IIS: DL1: HD1			DL1: HD1		✓
		HDMI2		IIS: DL1: HD2			DL1: HD2		✓
		S-VIDEO		IIS: DL1: SVD			DL1: SVD		✓
	FREEZE	OFF		OFZ: 0		QFZ	0		✓
		ON		OFZ: 1			1		✓
	MENU KEY			OMN					✓
	ENTER KEY			OEN					✓
	UP KEY			OCU					✓
	DOWN KEY			OCD					✓
	LEFT KEY			OCL					✓
	RIGHT KEY			OCR					✓
	DEFAULT KEY			OST					✓
	AUTO SETUP KEY			OAS					✓
	SHUTTER	ON		OSH: 0		QSH	0		✓
		OFF		OSH: 1			1		✓
	SHUTTER(Toggle)	OFF		OSH		QSH	0		✓
		ON					1		✓
	FUNCTION KEY			FC1					✓
	SYSTEM SELECTOR KEY			OSL					✓
	ASPECT KEY			VS1					✓
	NUMERIC KEY	0		ONK: 0					✓
		1		ONK: 1					✓
		2		ONK: 2					✓
		3		ONK: 3					✓
		4		ONK: 4					✓
		5		ONK: 5					✓
		6		ONK: 6					✓
		7		ONK: 7					✓
		8		ONK: 8					✓
		9		ONK: 9					✓
	LENS HOME POSITION	EXECUTE		VXX: LNSI 1=+00001					✓
	LENS SHIFT-HORIZONTAL	SLOW+		VXX: LNSI 2=+00000					✓
		SLOW-		VXX: LNSI 2=+00001					✓
		NORMAL+		VXX: LNSI 2=+00100					✓
		NORMAL-		VXX: LNSI 2=+00101					✓
		FAST+		VXX: LNSI 2=+00200					✓
		FAST-		VXX: LNSI 2=+00201					✓
LENS SHIFT-VERTICAL	SLOW+		VXX: LNSI 3=+00000					✓	
	SLOW-		VXX: LNSI 3=+00001					✓	
	NORMAL+		VXX: LNSI 3=+00100					✓	
	NORMAL-		VXX: LNSI 3=+00101					✓	
	FAST+		VXX: LNSI 3=+00200					✓	
	FAST-		VXX: LNSI 3=+00201					✓	
LENS FOCUS	SLOW+		VXX: LNSI 4=+00000					✓	
	SLOW-		VXX: LNSI 4=+00001					✓	
	NORMAL+		VXX: LNSI 4=+00100					✓	
	NORMAL-		VXX: LNSI 4=+00101					✓	
	FAST+		VXX: LNSI 4=+00200					✓	
	FAST-		VXX: LNSI 4=+00201					✓	
LENS ZOOM	SLOW+		VXX: LNSI 5=+00000					✓	
	SLOW-		VXX: LNSI 5=+00001					✓	
	NORMAL+		VXX: LNSI 5=+00100					✓	
	NORMAL-		VXX: LNSI 5=+00101					✓	
	FAST+		VXX: LNSI 5=+00200					✓	
	FAST-		VXX: LNSI 5=+00201					✓	
STATUS KEY			STS					✓	
LENS FOCUS KEY			OLF					✓	
LENS SHIFT KEY			OLH					✓	
LENS ZOOM KEY			OLZ					✓	
DIGITAL LINK KEY			DLK					✓	
INPUT MENU KEY			IPT					✓	
PICTURE MODE	DYNAMIC		VPM: DYN		QPM	DYN		✓	
	NATURAL		VPM: NAT			NAT		✓	
	STANDARD		VPM: STD			STD		✓	
	CINEMA		VPM: CIN			CIN		✓	
	GRAPHIC		VPM: GRA			GRA		✓	
	DICOM SIM.		VPM: DI C			DI C		✓	
	USER		VPM: USR			USR		✓	
	REC709		VPM: 709			709		✓	
	CONTRAST	+1		VCN: 001		QVR	001		✓
		+63		VCN: 063			063		✓
BRIGHTNESS	+1		VBR: 001		QVB	001		✓	
	+63		VBR: 063			063		✓	
COLOR	+1		VCO: 001		QVC	001		✓	
	+63		VCO: 063			063		✓	
TINT	+1		VTN: 001		QVT	001		✓	
	+63		VTN: 063			063		✓	
SHARPNESS	0		VSR: 000		QVS	000		✓	
	15		VSR: 015			015		✓	
WHITE GAIN	0		VWH: 00		QWH	00		✓	
	10		VWH: 10			10		✓	
COLOR TEMPERATURE	USER1(USER)		OTE: 04		QTE	4		✓	
	USER2		OTE: 09			9		✓	
	DEFAULT		OTE: 10			10		✓	
	3200K		OTE: 3200			3200		✓	
	3300K		OTE: 3300			3300		✓	
	9200K		OTE: 9200			9200		✓	
	9300K		OTE: 9300			9300		✓	
COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX: NCGS1=COLORTEMP1		QVX: NCGS1	NCGS1=COLORTEMP1		✓	
COLOR TEMP-NAME SETTING USER2	COLORTEMP2		VXX: NCGS3=COLORTEMP2		QVX: NCGS3	NCGS3=COLORTEMP2		✓	
COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX: NCLI 1=+00000					✓	
COLOR TEMP-NAME CLEAR USER2	COLORTEMP2		VXX: NCLI 3=+00000					✓	
WHITE BALANCE LOW-RED	-127		VOR: 001		QOR	001		✓	
	+127		VOR: 255			255		✓	
WHITE BALANCE LOW-GREEN	-127		VOG: 001		QOG	001		✓	
	+127		VOG: 255			255		✓	
WHITE BALANCE LOW-BLUE	-127		VOB: 001		QOB	001		✓	
	+127		VOB: 255			255		✓	
WHITE BALANCE HIGH-RED	0		VHR: 000		QHR	000		✓	
	+255		VHR: 255			255		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C
PICTURE	WHITE BALANCE HIGH-GREEN	0 +255		VHG: 000 VHG: 255	QHG	000 255	✓ ✓
	WHITE BALANCE HIGH-BLUE	0 +255		VHB: 000 VHB: 255	QHB	000 255	✓ ✓
	GAMMA	1.8		VGA: 1. 8	QGA	1. 8	✓
		2.0		VGA: 2. 0		2. 0	✓
		2.2		VGA: 2. 2		2. 2	✓
		USER1		VGA: US1		US1	✓
		DEFAULT		VGA: DEF		DEF	✓
	GAMMA-NAME SETTING USER1	GAMMAUSER1		VXX: NCGS2=GAMMAUSER1	QVX: NCGS2	NCGS2=GAMMAUSER1	✓
	GAMMA-NAME CLEAR USER1	GAMMAUSER1		VXX: NCLI 2=+00000			✓
	DAYLIGHT VIEW FRONT INSTALL	OFF		VXX: DLVI 0=+00000	QVX: DLVI 0	DLVI 0=+00000	✓
		AUTO(1)		VXX: DLVI 0=+00001		DLVI 0=+00001	✓
		ON(2)		VXX: DLVI 0=+00002		DLVI 0=+00002	✓
		ON(3)		VXX: DLVI 0=+00003		DLVI 0=+00003	✓
		4		VXX: DLVI 0=+00004		DLVI 0=+00004	✓
		5		VXX: DLVI 0=+00005		DLVI 0=+00005	✓
		6		VXX: DLVI 0=+00006		DLVI 0=+00006	✓
	NOISE REDUCTION	OFF		VNS: 0	QNS	0	✓
		1		VNS: 1		1	✓
		2		VNS: 2		2	✓
		3		VNS: 3		3	✓
	DYNAMIC CONTRAST/IRIS	OFF		OAI: 0	QAI	0	✓
		1		OAI: 1		1	✓
		2		OAI: 2		2	✓
		3		OAI: 3		3	✓
		USER		OAI: 4		4	✓
	DYNAMIC CONTRAST/AUTO IRIS (AUTO CONTRAST)	OFF		OAI: A000	QAI: A	000	✓
		1		OAI: A001		001	✓
		255		OAI: A255		255	✓
	DYNAMIC CONTRAST (BRIGHT SIGNAL LEVEL)	6%		VXX: DYCI 1=+00006	QVX: DYCI 1	00006	✓
		50%		VXX: DYCI 1=+00050		00050	✓
	DYNAMIC CONTRAST (LIGHTS OUT TIMER)	DISABLE		VXX: DYCS2=OFF	QVX: DYCS2	OFF	✓
		0.0s		VXX: DYCS2=0. 0		0. 0	✓
		10.0s		VXX: DYCS2=10. 0		10. 0	✓
	DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF		OAI: M000	QAI: M	000	✓
		1		OAI: M001		001	✓
		255		OAI: M255		255	✓
	DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF		OAI: D0	QAI: D	0	✓
		1		OAI: D1		1	✓
		2		OAI: D2		2	✓
		3		OAI: D3		3	✓
	TV-SYSTEM	AUTO1		VSG: AT1	QSG	AT1	✓
		AUTO2		VSG: AT2		AT2	✓
		NTSC		VSG: NTS		NTS	✓
		NTSC4.43		VSG: N44		N44	✓
		PAL		VSG: PAL		PAL	✓
		PAL-M		VSG: PAM		PAM	✓
		PAL-N		VSG: PAN		PAN	✓
PAL60			VSG: P60		P60	✓	
SECAM			VSG: SEC		SEC	✓	
SYSTEM SELECTOR RGB(VGA/480P)		VGA60		ORF: 0	QRF	0	✓
	480P(YCbCr)		ORF: 1		1	✓	
	480p(RGB)		ORF: 3		3	✓	
SYSTEM SELECTOR RGB(Other)/DVI/SLOT-DVI	RGB		ORF: 0	QRF	0	✓	
	YPbPr		ORF: 1		1	✓	
SYSTEM SELECTOR HDMI/DIGITAL LINK/SLOT-HDMI	RGB		ORF: 0	QRF	0	✓	
	YPbPr		ORF: 1		1	✓	
SYSTEM SELECTOR-SDI1 (SINGLE)	AUTO		ORF: 2	QSD	2	✓	
	480i YCbCr		VSD: 0		0	✓	
	576i YCbCr		VSD: 1		1	✓	
	1080/60i YPbPr		VSD: 3		3	✓	
	720/60p YPbPr		VSD: 4		4	✓	
	1080/24p YPbPr		VSD: 6		6	✓	
	1080/50i YpBpR		VSD: 7		7	✓	
	1080/30p YPbPr		VSD: 8		8	✓	
	1080/25p YPbPr		VSD: 9		9	✓	
	1080/24sF YPbPr		VSD: 10		10	✓	
	720/50p YPbPr		VSD: 11		11	✓	
	1080/50p YPbPr		VSD: 12		12	✓	
	1080/60p YPbPr		VSD: 15		15	✓	
	1080/24p RGB		VSD: 16		16	✓	
	1080/24sF RGB		VSD: 21		21	✓	
	1080/25p RGB		VSD: 22		22	✓	
	1080/30p RGB		VSD: 23		23	✓	
	1080/50i RGB		VSD: 24		24	✓	
	1080/60i RGB		VSD: 25		25	✓	
	2K25p RGB		VSD: 26		26	✓	
	2K/30p RGB		VSD: 33		33	✓	
			VSD: 34		34	✓	
GEOMETRY	OFF		VXX: GMMI 0=+00000	QVX: GMMI 0	GMMI 0=+00000	✓	
	KEYSTONE		VXX: GMMI 0=+00001		GMMI 0=+00001	✓	
	CURVED		VXX: GMMI 0=+00002		GMMI 0=+00002	✓	
	PC-1		VXX: GMMI 0=+00003		GMMI 0=+00003	✓	
	PC-2		VXX: GMMI 0=+00004		GMMI 0=+00004	✓	
	PC-3		VXX: GMMI 0=+00005		GMMI 0=+00005	✓	
	CORNER-CORRECTION		VXX: GMMI 0=+00010		GMMI 0=+00010	✓	
	GEOMETRY-KEYSTONE-LENS THROW RATIO	0.7	0.1 step	VXX: GMKSO=+00. 7	QVX: GMKSO	GMKSO=+00. 7	✓
		16.5		VXX: GMKSO=+16. 5		GMKSO=+16. 5	✓
	GEOMETRY-KEYSTONE-VERTICAL BALANCE	-60		VXX: GMKI 4=- 00060	QVX: GMKI 4	GMKI 4=- 00060	✓
		+60		VXX: GMKI 4=+00060		GMKI 4=+00060	✓
	GEOMETRY-KEYSTONE-HORIZONTAL BALANCE	-30		VXX: GMKI 7=- 00030	QVX: GMKI 7	GMKI 7=- 00030	✓
		+30		VXX: GMKI 7=+00030		GMKI 7=+00030	✓
	GEOMETRY-KEYSTONE-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX: GMKS8=- 40. 0	QVX: GMKS8	GMKS8=- 40. 0	✓
		+40.0 (+45.0)*		VXX: GMKS8=+40. 0		GMKS8=+40. 0	✓
	GEOMETRY-KEYSTONE-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX: GMKS9=- 15. 0	QVX: GMKS9	GMKS9=- 15. 0	✓
		+15.0 (+40.0)*		VXX: GMKS9=+15. 0		GMKS9=+15. 0	✓
	GEOMETRY-CURVED-LENS THROW RATIO	0.7	0.1 step	VXX: GMCS0=+00. 7	QVX: GMCS0	GMCS0=+00. 7	✓
		16.5		VXX: GMCS0=+16. 5		GMCS0=+16. 5	✓
	GEOMETRY-CURVED-VERTICAL ARC	-50 (-100)*		VXX: GMCI 3=- 00050	QVX: GMCI 3	GMCI 3=- 00050	✓
		+50 (+100)*		VXX: GMCI 3=+00050		GMCI 3=+00050	✓
	GEOMETRY-CURVED-HORIZONTAL ARC	-50 (-100)*		VXX: GMCI 7=- 00050	QVX: GMCI 7	GMCI 7=- 00050	✓
		+50 (+100)*		VXX: GMCI 7=+00050		GMCI 7=+00050	✓
	GEOMETRY-CURVED-VERTICAL BALANCE	-60		VXX: GMCI 2=- 00060	QVX: GMCI 2	GMCI 2=- 00060	✓
		+60		VXX: GMCI 2=+00060		GMCI 2=+00060	✓
	GEOMETRY-CURVED-HORIZONTAL BALANCE	-30		VXX: GMCI 6=- 00030	QVX: GMCI 6	GMCI 6=- 00030	✓
		+30		VXX: GMCI 6=+00030		GMCI 6=+00030	✓
GEOMETRY-CURVED-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX: GMCS8=- 40. 0	QVX: GMCS8	GMCS8=- 40. 0	✓	
	+40.0 (+45.0)*		VXX: GMCS8=+40. 0		GMCS8=+40. 0	✓	
GEOMETRY-CURVED-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX: GMCS9=- 15. 0	QVX: GMCS9	GMCS9=- 15. 0	✓	
	+15.0 (+40.0)*		VXX: GMCS9=+15. 0		GMCS9=+15. 0	✓	
GEOMETRY-CURVED-MAINTAIN ASPECT RATIO	OFF		VXX: GMCI A=+00000	QVX: GMCI A	GMCI A=+00000	✓	
	ON		VXX: GMCI A=+00001		GMCI A=+00001	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		RZ870 SERIES
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C	
POSITION	GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min.		VXX: GMFI 1=+00000	QVX: GMFI 1	GMFI 1=+00000	0	0
		max.		VXX: GMFI 1=+00300		GMFI 1=+00300	+300	+300
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min.		VXX: GMFI 2=+00000	QVX: GMFI 2	GMFI 2=+00000	0	0
		max.		VXX: GMFI 2=+00300		GMFI 2=+00300	+300	+300
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min.		VXX: GMFI 3=- 00300	QVX: GMFI 3	GMFI 3=- 00300	-300	-300
		max.		VXX: GMFI 3=+00000		GMFI 3=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min.		VXX: GMFI 4=- 00300	QVX: GMFI 4	GMFI 4=- 00300	-300	-300
		max.		VXX: GMFI 4=+00000		GMFI 4=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min.		VXX: GMFI 5=- 00127	QVX: GMFI 5	GMFI 5=- 00127	-127	-127
		max.		VXX: GMFI 5=+00127		GMFI 5=+00127	+127	+127
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min.		VXX: GMFI 6=+00000	QVX: GMFI 6	GMFI 6=+00000	0	0
		max.		VXX: GMFI 6=+00480		GMFI 6=+00480	+480	+480
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min.		VXX: GMFI 7=- 00480	QVX: GMFI 7	GMFI 7=- 00480	-480	-480
		max.		VXX: GMFI 7=+00000		GMFI 7=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min.		VXX: GMFI 8=+00000	QVX: GMFI 8	GMFI 8=+00000	0	0
		max.		VXX: GMFI 8=+00480		GMFI 8=+00480	+480	+480
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min.		VXX: GMFI 9=- 00480	QVX: GMFI 9	GMFI 9=- 00480	-480	-480
		max.		VXX: GMFI 9=+00000		GMFI 9=+00000	0	0
	GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min.		VXX: GMFI A=- 00127	QVX: GMFI A	GMFI A=- 00127	-127	-127
		max.		VXX: GMFI A=+00127		GMFI A=+00127	+127	+127
SHIFT-HORIZONTAL	0		VTH: 0000	QTH	0000	0	0	
	+4095		VTH: 4095		4095	4095	4095	
SHIFT-VERTICAL	0		VTV: 0000	QTV	0000	0	0	
	+4094		VTV: 4094		4094	4094	4094	
CLOCK PHASE	0		VCP: 000	QCP	000	0	0	
	+31		VCP: 031		063	063	063	
ASPECT	AUTO/VID AUTO/DEFAULT		VSE: 0	QSE	0	0	0	
	NORMAL(4:3)		VSE: 1		1	1	1	
	WIDE(16:9)		VSE: 2		2	2	2	
	NATIVE(through)		VSE: 5		5	5	5	
	FULL(HV FIT)		VSE: 6		6	6	6	
	H-FIT		VSE: 9		9	9	9	
	V-FIT		VSE: 10		10	10	10	
ZOOM-HORIZONTAL	50		OZH: 050	QZH	050	050	050	
	999		OZH: 999		999	999	999	
ZOOM-VERTICAL	50		OZV: 050	QZV	050	050	050	
	999		OZV: 999		999	999	999	
ZOOM-BOTH	50		OZO: 050	QZO	050	050	050	
	999		OZO: 999		999	999	999	
ZOOM-INTERLOCKED	OFF		OZS: 0	QZS	0	0	0	
	ON		OZS: 1		1	1	1	
ZOOM-MODE	INTERNAL		OZT: 0	QZT	0	0	0	
	FULL		OZT: 1		1	1	1	
ADVANCED	DIGITAL CINEMA REALITY	AUTO		OPD: 0	QPD	0	0	0
		OFF		OPD: 1		1	1	1
		30p/25p FIXED		OPD: 2		2	2	2
	BLANKING-UPPER	min.		DBU: 000	QLU	000	0	0
		max.		DBU: 2398		2398	2398	2398
	BLANKING-LOWER	min.		DBB: 000	QLB	000	0	0
		max.		DBB: 2398		2398	2398	2398
	BLANKING-RIGHT	min.		DBR: 000	QLR	000	0	0
		max.		DBR: 3838		3838	3838	3838
	BLANKING-LEFT	min.		DBL: 000	QLL	000	0	0
		max.		DBL: 3838		3838	3838	3838
	INPUT RESOLUTION-TOTAL DOTS	330		VTD: 0330	QTD	0330	0330	0330
		4095		VTD: 4095		4095	4095	4095
	INPUT RESOLUTION-DISPLAY DOTS	300		VDD: 0300	QDD	0300	0300	0300
		4065		VDD: 4065		4065	4065	4065
	INPUT RESOLUTION-TOTAL LINES	155		VTL: 0155	QTL	0155	0155	0155
		2047		VTL: 2047		2047	2047	2047
	INPUT RESOLUTION-DISPLAY LINES	150		VDL: 0150	QDL	0150	0150	0150
		2037		VDL: 2037		2037	2037	2037
	CLAMP POSITION	1		VLT: 001	QLT	001	001	001
		255		VLT: 255		255	255	255
	CUSTOM MASKING *	OFF		VXX: MSKI 1=+00000	QVX: MSKI 1	MSKI 1=+00000	MSKI 1=+00000	MSKI 1=+00000
		PC-1		VXX: MSKI 1=+00001		MSKI 1=+00001	MSKI 1=+00001	MSKI 1=+00001
		PC-2		VXX: MSKI 1=+00002		MSKI 1=+00002	MSKI 1=+00002	MSKI 1=+00002
		PC-3		VXX: MSKI 1=+00003		MSKI 1=+00003	MSKI 1=+00003	MSKI 1=+00003
	EDGE BLENDING	OFF		VXX: EDBI 0=+00000	QVX: EDBI 0	EDBI 0=+00000	EDBI 0=+00000	EDBI 0=+00000
		ON		VXX: EDBI 0=+00001		EDBI 0=+00001	EDBI 0=+00001	EDBI 0=+00001
		USER		VXX: EDBI 0=+00002		EDBI 0=+00002	EDBI 0=+00002	EDBI 0=+00002
	EDGE BLENDING-UPPER ON/OFF	OFF		VGU: 0	QGU	0	0	0
		ON		VGU: 1		1	1	1
	EDGE BLENDING-LOWER ON/OFF	OFF		VGB: 0	QGB	0	0	0
		ON		VGB: 1		1	1	1
	EDGE BLENDING-LEFT ON/OFF	OFF		VGL: 0	QGL	0	0	0
		ON		VGL: 1		1	1	1
	EDGE BLENDING-RIGHT ON/OFF	OFF		VGR: 0	QGR	0	0	0
		ON		VGR: 1		1	1	1
	EDGE BLENDING-START-UPPER	min.		VEU: 0000	QEU	0000	0000	0000
		max.		VEU: 2272		2272	2272	2272
	EDGE BLENDING-START-LOWER	min.		VEB: 0000	QEB	0000	0000	0000
		max.		VEB: 2272		2272	2272	2272
EDGE BLENDING-START-LEFT	min.		VEL: 0000	QEL	0000	0000	0000	
	max.		VEL: 3712		3712	3712	3712	
EDGE BLENDING-START-RIGHT	min.		VER: 0000	QER	0000	0000	0000	
	max.		VER: 3712		3712	3712	3712	
EDGE BLENDING-WIDTH-UPPER	min.		VXX: EUWI 0=+00000	QVX: EUWI 0	EUWI 0=+00000	EUWI 0=+00000	EUWI 0=+00000	
	max.		VXX: EUWI 0=+02272		EUWI 0=+02272	EUWI 0=+02272	EUWI 0=+02272	
EDGE BLENDING-WIDTH-LOWER	min.		VXX: EBWI 0=+00000	QVX: EBWI 0	EBWI 0=+00000	EBWI 0=+00000	EBWI 0=+00000	
	max.		VXX: EBWI 0=+02272		EBWI 0=+02272	EBWI 0=+02272	EBWI 0=+02272	
EDGE BLENDING-WIDTH-LEFT	min.		VXX: ELWI 0=+00000	QVX: ELWI 0	ELWI 0=+00000	ELWI 0=+00000	ELWI 0=+00000	
	max.		VXX: ELWI 0=+03712		ELWI 0=+03712	ELWI 0=+03712	ELWI 0=+03712	
EDGE BLENDING-WIDTH-RIGHT	min.		VXX: ERWI 0=+00000	QVX: ERWI 0	ERWI 0=+00000	ERWI 0=+00000	ERWI 0=+00000	
	max.		VXX: ERWI 0=+03712		ERWI 0=+03712	ERWI 0=+03712	ERWI 0=+03712	
EDGE BLENDING-MARKER-ON/OFF	OFF		VGM: 0	QGM	0	0	0	
	ON		VGM: 1		1	1	1	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	0 (W,R,G,B)		VJI: 000.000.000.000	QJI	000.000.000.000	000.000.000.000	000.000.000.000	
	255 (W,R,G,B)		VJI: 255.255.255.255		255.255.255.255	255.255.255.255	255.255.255.255	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-	OFF		VXX: EBI I 1=+00000	QVX: EBI I 1	EBI I 1=+00000	EBI I 1=+00000	EBI I 1=+00000	
	ON		VXX: EBI I 1=+00001		EBI I 1=+00001	EBI I 1=+00001	EBI I 1=+00001	
EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B)		VJO: 000.000.000.000	QJO	000.000.000.000	000.000.000.000	000.000.000.000	
	255 (W,R,G,B)		VJO: 255.255.255.255		255.255.255.255	255.255.255.255	255.255.255.255	
EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF		VXX: EBI I 2=+00000	QVX: EBI I 2	EBI I 2=+00000	EBI I 2=+00000	EBI I 2=+00000	
	ON		VXX: EBI I 2=+00001		EBI I 2=+00001	EBI I 2=+00001	EBI I 2=+00001	
EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min.		VJU: 0000	QJU	0000	0000	0000	
	max.		VJU: 2272		2272	2272	2272	
EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min.		VJB: 0000	QJB	0000	0000	0000	
	max.		VJB: 2272		2272	2272	2272	
EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min.		VJL: 0000	QJL	0000	0000	0000	
	max.		VJL: 3712		3712	3712	3712	
EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min.		VJR: 0000	QJR	0000	0000	0000	
	max.		VJR: 3712		3712	3712	3712	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C	
EDGE BLENDING	EDGE BLENDING-BLACK BORDER WIDTH-UPPER KEYSTONE AREA	min. max.		VXX: EBBI 4=- 02272 VXX: EBBI 4+=02272	QVX: EBBI 4	EBBI 4=- 02272 EBBI 4+=02272	-1199 1919	
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER KEYSTONE AREA	min. max.		VXX: EBBI 5=- 02272 VXX: EBBI 5+=02272	QVX: EBBI 5	EBBI 5=- 02272 EBBI 5+=02272	-1199 1919	
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT KEYSTONE AREA	min. max.		VXX: EBBI 6=- 03712 VXX: EBBI 6+=03712	QVX: EBBI 6	EBBI 6=- 03712 EBBI 6+=03712	-1199 1919	
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT KEYSTONE AREA	min. max.		VXX: EBBI 7=- 03712 VXX: EBBI 7+=03712	QVX: EBBI 7	EBBI 7=- 03712 EBBI 7+=03712	-1199 1919	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B) 255 (W,R,G,B)		VXX: EBBS0=000, 000, 000, 000 VXX: EBBS0=255, 255, 255, 255	QVX: EBBS0	EBBS0=000, 000, 000, 000 EBBS0=255, 255, 255, 255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	0 (W,R,G,B) 255 (W,R,G,B)		VXX: EBBS1=000, 000, 000, 000 VXX: EBBS1=255, 255, 255, 255	QVX: EBBS1	EBBS1=000, 000, 000, 000 EBBS1=255, 255, 255, 255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B) 255 (W,R,G,B)		VXX: EBBS2=000, 000, 000, 000 VXX: EBBS2=255, 255, 255, 255	QVX: EBBS2	EBBS2=000, 000, 000, 000 EBBS2=255, 255, 255, 255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B) 255 (W,R,G,B)		VXX: EBBS3=000, 000, 000, 000 VXX: EBBS3=255, 255, 255, 255	QVX: EBBS3	EBBS3=000, 000, 000, 000 EBBS3=255, 255, 255, 255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	OFF ON		VXX: EBBI 3+=00000 VXX: EBBI 3+=00001	QVX: EBBI 3	EBBI 3+=00000 EBBI 3+=00001	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	OFF ON		VXX: EBBI 4+=00000 VXX: EBBI 4+=00001	QVX: EBBI 4	EBBI 4+=00000 EBBI 4+=00001	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF ON		VXX: EBBI 5+=00000 VXX: EBBI 5+=00001	QVX: EBBI 5	EBBI 5+=00000 EBBI 5+=00001	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	OFF ON		VXX: EBBI 6+=00000 VXX: EBBI 6+=00001	QVX: EBBI 6	EBBI 6+=00000 EBBI 6+=00001	✓ ✓	
	EDGE BLENDING-AUTO TESTPATTERN	OFF ON		VXX: EATI 1+=00000 VXX: EATI 1+=00001	QVX: EATI 1	EATI 1+=00000 EATI 1+=00001	✓ ✓	
	FRAME RESPONSE	NORMAL FAST FIXED		VXX: FDYI 0+=00000 VXX: FDYI 0+=00001 VXX: FDYI 0+=00005	QVX: FDYI 0	FDYI 0+=00000 FDYI 0+=00001 FDYI 0+=00005	✓ ✓ ✓	
	RASTER POSITION-HORIZONTAL	-2048 +2047		VRH: 2952 VRH: 7047	QRH	2952 7047	✓ ✓	
	RASTER POSITION-VERTICAL	-2048 +2047		VRV: 2952 VRV: 7047	QRV	2952 7047	✓ ✓	
	DISPLAY LANGUAGE	LANGUAGE	English German French Spanish Italian Japanese Chinese Russian Korea Portuguse		OLG: ENG OLG: DEU OLG: FRA OLG: ESP OLG: I TL OLG: JPN OLG: CHI OLG: RUS OLG: KOR OLG: POR	QLG	ENG DEU FRA ESP I TL JPN CHI RUS KOR POR	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
		COLOR MATCHING	OFF 3COLORS 7COLORS MEASURED		VXX: CMAI 0+=00000 VXX: CMAI 0+=00001 VXX: CMAI 0+=00002 VXX: CMAI 0+=00004	QVX: CMAI 0	CMAI 0+=00000 CMAI 0+=00001 CMAI 0+=00002 CMAI 0+=00004	✓ ✓ ✓ ✓
		COLOR MATCHING-3COLORS-RED	0 (R,G,B) 2048,2048,2048(R,G,B)		VMR: 0000, 0000, 0000 VMR: 2048, 2048, 2048	QMR	0000, 0000, 0000 2048, 2048, 2048	✓ ✓
		COLOR MATCHING-3COLORS-GREEN	0 (R,G,B) 2048,2048,2048(R,G,B)		VMG: 0000, 0000, 0000 VMG: 2048, 2048, 2048	QMG	0000, 0000, 0000 2048, 2048, 2048	✓ ✓
		COLOR MATCHING-3COLORS-BLUE	0 (R,G,B) 2048,2048,2048(R,G,B)		VMB: 0000, 0000, 0000 VMB: 2048, 2048, 2048	QMB	0000, 0000, 0000 2048, 2048, 2048	✓ ✓
		COLOR MATCHING-3COLORS-WHITE	256 (GAIN) 2048(GAIN)		VMM: 0256 VMM: 2048	QMW	0256 2048	✓ ✓
		COLOR MATCHING-3COLORS-AUTO TESTPATTERN	OFF ON		VXX: CATI 0+=00000 VXX: CATI 0+=00001	QVX: CATI 0	CATI 0+=00000 CATI 0+=00001	✓ ✓
		COLOR MATCHING-7COLORS-RED	0 (R,G,B) 2048(R,G,B)		VXX: C7CS0=0000, 0000, 0000 VXX: C7CS0=2048, 2048, 2048	QVX: C7CS0	C7CS0=0000, 0000, 0000 C7CS0=2048, 2048, 2048	✓ ✓
		COLOR MATCHING-7COLORS-GREEN	0 (R,G,B) 2048(R,G,B)		VXX: C7CS1=0000, 0000, 0000 VXX: C7CS1=2048, 2048, 2048	QVX: C7CS1	C7CS1=0000, 0000, 0000 C7CS1=2048, 2048, 2048	✓ ✓
		COLOR MATCHING-7COLORS-BLUE	0 (R,G,B) 2048(R,G,B)		VXX: C7CS2=0000, 0000, 0000 VXX: C7CS2=2048, 2048, 2048	QVX: C7CS2	C7CS2=0000, 0000, 0000 C7CS2=2048, 2048, 2048	✓ ✓
	COLOR MATCHING-7COLORS-CYAN	0 (R,G,B) 2048(R,G,B)		VXX: C7CS3=0000, 0000, 0000 VXX: C7CS3=2048, 2048, 2048	QVX: C7CS3	C7CS3=0000, 0000, 0000 C7CS3=2048, 2048, 2048	✓ ✓	
	COLOR MATCHING-7COLORS-MAGENTA	0 (R,G,B) 2048(R,G,B)		VXX: C7CS4=0000, 0000, 0000 VXX: C7CS4=2048, 2048, 2048	QVX: C7CS4	C7CS4=0000, 0000, 0000 C7CS4=2048, 2048, 2048	✓ ✓	
	COLOR MATCHING-7COLORS-YELLOW	0 (R,G,B) 2048(R,G,B)		VXX: C7CS5=0000, 0000, 0000 VXX: C7CS5=2048, 2048, 2048	QVX: C7CS5	C7CS5=0000, 0000, 0000 C7CS5=2048, 2048, 2048	✓ ✓	
	COLOR MATCHING-7COLORS-WHITE	0 (R,G,B) 2048(R,G,B)		VXX: C7CS6=0000, 0000, 0000 VXX: C7CS6=2048, 2048, 2048	QVX: C7CS6	C7CS6=0000, 0000, 0000 C7CS6=2048, 2048, 2048	✓ ✓	
	COLOR MATCHING-7COLORS-AUTO TESTPATTERN	OFF ON		VXX: CATI 1+=00000 VXX: CATI 1+=00001	QVX: CATI 1	CATI 1+=00000 CATI 1+=00001	✓ ✓	
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS0=00000, 0001, 0001 VXX: CMMS0=65535, 0999, 0999	QVX: CMMS0	CMMS0=00000, 0001, 0001 CMMS0=65535, 0999, 0999	✓ ✓	
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS1=00000, 0001, 0001 VXX: CMMS1=65535, 0999, 0999	QVX: CMMS1	CMMS1=00000, 0001, 0001 CMMS1=65535, 0999, 0999	✓ ✓	
COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS2=00000, 0001, 0001 VXX: CMMS2=65535, 0999, 0999	QVX: CMMS2	CMMS2=00000, 0001, 0001 CMMS2=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS3=00000, 0001, 0001 VXX: CMMS3=65535, 0999, 0999	QVX: CMMS3	CMMS3=00000, 0001, 0001 CMMS3=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS4=00000, 0001, 0001 VXX: CMMS4=65535, 0999, 0999	QVX: CMMS4	CMMS4=00000, 0001, 0001 CMMS4=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS0=00000, 0001, 0001 VXX: CMMS0=65535, 0999, 0999	QVX: CMMS0	CMMS0=00000, 0001, 0001 CMMS0=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS1=00000, 0001, 0001 VXX: CMMS1=65535, 0999, 0999	QVX: CMMS1	CMMS1=00000, 0001, 0001 CMMS1=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS2=00000, 0001, 0001 VXX: CMMS2=65535, 0999, 0999	QVX: CMMS2	CMMS2=00000, 0001, 0001 CMMS2=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS3=00000, 0001, 0001 VXX: CMMS3=65535, 0999, 0999	QVX: CMMS3	CMMS3=00000, 0001, 0001 CMMS3=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS4=00000, 0001, 0001 VXX: CMMS4=65535, 0999, 0999	QVX: CMMS4	CMMS4=00000, 0001, 0001 CMMS4=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS5=00000, 0001, 0001 VXX: CMMS5=65535, 0999, 0999	QVX: CMMS5	CMMS5=00000, 0001, 0001 CMMS5=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y) 65535,999,999(Y,x,y)		VXX: CMMS6=00000, 0001, 0001 VXX: CMMS6=65535, 0999, 0999	QVX: CMMS6	CMMS6=00000, 0001, 0001 CMMS6=65535, 0999, 0999	✓ ✓		
COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF ON		VXX: CATI 3+=00000 VXX: CATI 3+=00001	QVX: CATI 3	CATI 3+=00000 CATI 3+=00001	✓ ✓		
COLOR CORRECTION	OFF USER		VCM: 0 VCM: 1	QMC	0 1	✓ ✓		
COLOR CORRECTION-RED	-30 +30		VXX: CCRI 0=- 00030 VXX: CCRI 0+=00030	QVX: CCRI 0	CCRI 0=- 00030 CCRI 0+=00030	✓ ✓		
COLOR CORRECTION-GREEN	-30 +30		VXX: CCRI 1=- 00030 VXX: CCRI 1+=00030	QVX: CCRI 1	CCRI 1=- 00030 CCRI 1+=00030	✓ ✓		
COLOR CORRECTION-BLUE	-30 +30		VXX: CCRI 2=- 00030 VXX: CCRI 2+=00030	QVX: CCRI 2	CCRI 2=- 00030 CCRI 2+=00030	✓ ✓		
COLOR CORRECTION-CYAN	-30 +30		VXX: CCRI 3=- 00030 VXX: CCRI 3+=00030	QVX: CCRI 3	CCRI 3=- 00030 CCRI 3+=00030	✓ ✓		
COLOR CORRECTION-MAGENTA	-30 +30		VXX: CCRI 4=- 00030 VXX: CCRI 4+=00030	QVX: CCRI 4	CCRI 4=- 00030 CCRI 4+=00030	✓ ✓		
COLOR CORRECTION-YELLOW	-30 +30		VXX: CCRI 5=- 00030 VXX: CCRI 5+=00030	QVX: CCRI 5	CCRI 5=- 00030 CCRI 5+=00030	✓ ✓		
AUTO SIGNAL	OFF		VXX: AASI 0+=00000	QVX: AASI 0	AASI 0+=00000	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C
DISPLAY OPTION	AUTO SETUP -MODE	ON		VXX: AASI 0=+00001		AASI 0=+00001	✓
		USER		OAM 0	QAM	0	✓
		DEFAULT		OAM 1		1	✓
	AUTO SETUP -POSITION ADJ.	WIDE		OAM 2		2	✓
		OFF		VXX: APAI 0=+00000	QVX: APAI 0	APAI 0=+00000	✓
		ON		VXX: APAI 0=+00001		APAI 0=+00001	✓
	AUTO SETUP -SIGNAL LEVEL ADJ.	OFF		VXX: ASLI 0=+00000	QVX: ASLI 0	ASLI 0=+00000	✓
		ON		VXX: ASLI 0=+00001		ASLI 0=+00001	✓
	BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY		VXX: BACI 1=+00001	QVX: BACI 1	BACI 1=+00001	✓
		SECONDARY		VXX: BACI 1=+00002		BACI 1=+00002	✓
		TOGGLE		VXX: BACI 1=+00010		BACI 1=+00010	✓
	BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF		VXX: BACI 2=+00000	QVX: BACI 2	BACI 2=+00000	✓
		ON/1		VXX: BACI 2=+00001		BACI 2=+00001	✓
	BACKUP INPUT SETTING-AUTOMATIC SWITCHING	DISABLE		VXX: BACI 3=+00001	QVX: BACI 3	BACI 3=+00001	✓
		ENABLE		VXX: BACI 3=+00002		BACI 3=+00002	✓
	BACKUP INPUT SETTING-BACKUP INPUT STATUS	INACTIVE			QVX: BACI 4	BACI 4=+00000	✓
		ACTIVE				BACI 4=+00001	✓
	RGB IN-RGB1 INPUT SETTING	RGB/YBPBR		VXX: RYCI 1=+00000	QVX: RYCI 1	RYCI 1=+00000	✓
		Y/C		VXX: RYCI 1=+00001		RYCI 1=+00001	✓
		VIDEO		VXX: RYCI 1=+00002		RYCI 1=+00002	✓
	RGB IN-RGB1 SYNC SLICE LEVEL	LOW		VXX: STRI 0=+00000	QVX: STRI 0	STRI 0=+00000	✓
		HIGH		VXX: STRI 0=+00001		STRI 0=+00001	✓
	RGB IN-RGB2 SYNC SLICE LEVEL	LOW		VXX: STRI 1=+00000	QVX: STRI 1	STRI 1=+00000	✓
		HIGH		VXX: STRI 1=+00001		STRI 1=+00001	✓
	RGB IN-RGB2 EDID MODE	DEFAULT		VXX: EDM1 1=+00000	QVX: EDM1 1	EDM1 1=+00000	✓
		SCREEB FIT		VXX: EDM1 1=+00001		EDM1 1=+00001	✓
		USER		VXX: EDM1 1=+00010		EDM1 1=+00010	✓
	RGB IN-RGB2 EDID RESOLUTION	1024x768p		VXX: EDRS1=1024: 0768: p	QVX: EDRS1	EDRS1=1024: 0768: p	✓
		1280x720p		VXX: EDRS1=1280: 0720: p		EDRS1=1280: 0720: p	✓
		1280x768p		VXX: EDRS1=1280: 0768: p		EDRS1=1280: 0768: p	✓
		1280x800p		VXX: EDRS1=1280: 0800: p		EDRS1=1280: 0800: p	✓
		1280x1024p		VXX: EDRS1=1280: 1024: p		EDRS1=1280: 1024: p	✓
		1366x768p		VXX: EDRS1=1366: 0768: p		EDRS1=1366: 0768: p	✓
		1400x1050p		VXX: EDRS1=1400: 1050: p		EDRS1=1400: 1050: p	✓
		1440x900p		VXX: EDRS1=1440: 0900: p		EDRS1=1440: 0900: p	✓
		1600x900p		VXX: EDRS1=1600: 0900: p		EDRS1=1600: 0900: p	✓
		1600x1200p		VXX: EDRS1=1600: 1200: p		EDRS1=1600: 1200: p	✓
		1680x1050p		VXX: EDRS1=1680: 1050: p		EDRS1=1680: 1050: p	✓
		1920x1080p		VXX: EDRS1=1920: 1080: p		EDRS1=1920: 1080: p	✓
		1920x1080i		VXX: EDRS1=1920: 1080: i		EDRS1=1920: 1080: i	✓
		1920x1200p		VXX: EDRS1=1920: 1200: p		EDRS1=1920: 1200: p	✓
		RGB IN-RGB2 EDID VERTICAL SCAN FREQUENCY	60Hz		VXX: EDVI 1=+06000	QVX: EDVI 1	EDVI 1=+06000
	50Hz			VXX: EDVI 1=+05000		EDVI 1=+05000	✓
	48Hz			VXX: EDVI 1=+04800		EDVI 1=+04800	✓
	30Hz			VXX: EDVI 1=+03000		EDVI 1=+03000	✓
	25Hz			VXX: EDVI 1=+02500		EDVI 1=+02500	✓
	24Hz			VXX: EDVI 1=+02400		EDVI 1=+02400	✓
DVI-D IN-EDID	EDID1		OED: 1	QED	1	✓	
	EDID2(PC)		OED: 2		2	✓	
	EDID3		OED: 3		3	✓	
DVI-D IN-SIGNAL LEVEL	0-255 PC		VXX: DVII 0=+00000	QVX: DVII 0	DVII 0=+00000	✓	
	15-235		VXX: DVII 0=+00001		DVII 0=+00001	✓	
	AUTO		VXX: DVII 0=+00002		DVII 0=+00002	✓	
DVI-D IN-EDID MODE	DEFAULT		VXX: EDM2 2=+00000	QVX: EDM2 0	EDM2 2=+00000	✓	
	SCREEN FIT		VXX: EDM2 2=+00001		EDM2 2=+00001	✓	
	USER		VXX: EDM2 2=+00010		EDM2 2=+00010	✓	
DVI-D IN-EDID RESOLUTION	1024x768p		VXX: EDRS2=1024: 0768: p	QVX: EDRS2	EDRS2=1024: 0768: p	✓	
	1280x720p		VXX: EDRS2=1280: 0720: p		EDRS2=1280: 0720: p	✓	
	1280x768p		VXX: EDRS2=1280: 0768: p		EDRS2=1280: 0768: p	✓	
	1280x800p		VXX: EDRS2=1280: 0800: p		EDRS2=1280: 0800: p	✓	
	1280x1024p		VXX: EDRS2=1280: 1024: p		EDRS2=1280: 1024: p	✓	
	1366x768p		VXX: EDRS2=1366: 0768: p		EDRS2=1366: 0768: p	✓	
	1400x1050p		VXX: EDRS2=1400: 1050: p		EDRS2=1400: 1050: p	✓	
	1440x900p		VXX: EDRS2=1440: 0900: p		EDRS2=1440: 0900: p	✓	
	1600x900p		VXX: EDRS2=1600: 0900: p		EDRS2=1600: 0900: p	✓	
	1600x1200p		VXX: EDRS2=1600: 1200: p		EDRS2=1600: 1200: p	✓	
	1680x1050p		VXX: EDRS2=1680: 1050: p		EDRS2=1680: 1050: p	✓	
	1920x1080p		VXX: EDRS2=1920: 1080: p		EDRS2=1920: 1080: p	✓	
	1920x1080i		VXX: EDRS2=1920: 1080: i		EDRS2=1920: 1080: i	✓	
	1920x1200p		VXX: EDRS2=1920: 1200: p		EDRS2=1920: 1200: p	✓	
	DVI-D IN-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX: EDVI 2=+06000	QVX: EDVI 2	EDVI 2=+06000	✓
50Hz			VXX: EDVI 2=+05000		EDVI 2=+05000	✓	
48Hz			VXX: EDVI 2=+04800		EDVI 2=+04800	✓	
30Hz			VXX: EDVI 2=+03000		EDVI 2=+03000	✓	
25Hz			VXX: EDVI 2=+02500		EDVI 2=+02500	✓	
24Hz			VXX: EDVI 2=+02400		EDVI 2=+02400	✓	
HDMI IN-SIGNAL LEVEL	0-1023		VXX: HSLI 0=+00000	QVX: HSLI 0	HSLI 0=+00000	✓	
	64-940		VXX: HSLI 0=+00001		HSLI 0=+00001	✓	
	AUTO		VXX: HSLI 0=+00002		HSLI 0=+00002	✓	
HDMI IN-EDID MODE	DEFAULT		VXX: EDM3 3=+00000	QVX: EDM3 3	EDM3 3=+00000	✓	
	SCREEN FIT		VXX: EDM3 3=+00001		EDM3 3=+00001	✓	
	USER		VXX: EDM3 3=+00010		EDM3 3=+00010	✓	
HDMI IN-EDID RESOLUTION	1024x768p		VXX: EDRS3=1024: 0768: p	QVX: EDRS3	EDRS3=1024: 0768: p	✓	
	1280x720p		VXX: EDRS3=1280: 0720: p		EDRS3=1280: 0720: p	✓	
	1280x768p		VXX: EDRS3=1280: 0768: p		EDRS3=1280: 0768: p	✓	
	1280x800p		VXX: EDRS3=1280: 0800: p		EDRS3=1280: 0800: p	✓	
	1280x1024p		VXX: EDRS3=1280: 1024: p		EDRS3=1280: 1024: p	✓	
	1366x768p		VXX: EDRS3=1366: 0768: p		EDRS3=1366: 0768: p	✓	
	1400x1050p		VXX: EDRS3=1400: 1050: p		EDRS3=1400: 1050: p	✓	
	1440x900p		VXX: EDRS3=1440: 0900: p		EDRS3=1440: 0900: p	✓	
	1600x900p		VXX: EDRS3=1600: 0900: p		EDRS3=1600: 0900: p	✓	
	1600x1200p		VXX: EDRS3=1600: 1200: p		EDRS3=1600: 1200: p	✓	
	1680x1050p		VXX: EDRS3=1680: 1050: p		EDRS3=1680: 1050: p	✓	
	1920x1080p		VXX: EDRS3=1920: 1080: p		EDRS3=1920: 1080: p	✓	
	1920x1080i		VXX: EDRS3=1920: 1080: i		EDRS3=1920: 1080: i	✓	
	1920x1200p		VXX: EDRS3=1920: 1200: p		EDRS3=1920: 1200: p	✓	
	HDMI IN-EDID VERTICAL SCAN FREQUENCY	60Hz		VXX: EDVI 3=+06000	QVX: EDVI 3	EDVI 3=+06000	✓
50Hz			VXX: EDVI 3=+05000		EDVI 3=+05000	✓	
48Hz			VXX: EDVI 3=+04800		EDVI 3=+04800	✓	
30Hz			VXX: EDVI 3=+03000		EDVI 3=+03000	✓	
25Hz			VXX: EDVI 3=+02500		EDVI 3=+02500	✓	
24Hz			VXX: EDVI 3=+02400		EDVI 3=+02400	✓	
DIGITAL LINK-SIGNAL LEVEL	AUTO		VXX: DKLI 1=+00000	QVX: DKLI 1	DKLI 1=+00000	✓	
	0-1023		VXX: DKLI 1=+00001		DKLI 1=+00001	✓	
	64-940		VXX: DKLI 1=+00002		DKLI 1=+00002	✓	
DIGITAL LINK-EDID MODE	DEFAULT		VXX: EDM4 4=+00000	QVX: EDM4 4	EDM4 4=+00000	✓	
	SCREEN FIT		VXX: EDM4 4=+00001		EDM4 4=+00001	✓	
	USER		VXX: EDM4 4=+00010		EDM4 4=+00010	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C	
DIGITAL LINK-EDID RESOLUTION	1024x768p			VXX: EDRS4=1024: 0768: p	QVX: EDRS4	EDRS4=1024: 0768: p	✓	
	1280x720p			VXX: EDRS4=1280: 0720: p		EDRS4=1280: 0720: p	✓	
	1280x768p			VXX: EDRS4=1280: 0768: p		EDRS4=1280: 0768: p	✓	
	1280x800p			VXX: EDRS4=1280: 0800: p		EDRS4=1280: 0800: p	✓	
	1280x1024p			VXX: EDRS4=1280: 1024: p		EDRS4=1280: 1024: p	✓	
	1366x768p			VXX: EDRS4=1366: 0768: p		EDRS4=1366: 0768: p	✓	
	1400x1050p			VXX: EDRS4=1400: 1050: p		EDRS4=1400: 1050: p	✓	
	1440x900p			VXX: EDRS4=1440: 0900: p		EDRS4=1440: 0900: p	✓	
	1600x900p			VXX: EDRS4=1600: 0900: p		EDRS4=1600: 0900: p	✓	
	1600x1200p			VXX: EDRS4=1600: 1200: p		EDRS4=1600: 1200: p	✓	
	1680x1050p			VXX: EDRS4=1680: 1050: p		EDRS4=1680: 1050: p	✓	
	1920x1080p			VXX: EDRS4=1920: 1080: p		EDRS4=1920: 1080: p	✓	
	1920x1080i			VXX: EDRS4=1920: 1080: i		EDRS4=1920: 1080: i	✓	
	1920x1200p			VXX: EDRS4=1920: 1200: p		EDRS4=1920: 1200: p	✓	
	DIGITAL LINK-EDID VERTICAL SCAN FREQUENCY	60Hz			VXX: EDVI 4=+06000	QVX: EDVI 4	EDVI 4=+06000	✓
		50Hz			VXX: EDVI 4=+05000		EDVI 4=+05000	✓
		48Hz			VXX: EDVI 4=+04800		EDVI 4=+04800	✓
		30Hz			VXX: EDVI 4=+03000		EDVI 4=+03000	✓
		25Hz			VXX: EDVI 4=+02500		EDVI 4=+02500	✓
24Hz			VXX: EDVI 4=+02400		EDVI 4=+02400	✓		
SDI IN-SIGNAL LEVEL	64-940			OED: SDI - LEVEL0	QED: SDI - LEVEL	0	✓	
	4-1019			OED: SDI - LEVEL1		1	✓	
SDI IN-SIGNAL LEVEL (SDI1)	64-940			VXX: SSLI 1=+00000	QVX: SSLI 1	SSLI 1=+00000	✓	
	4-1019			VXX: SSLI 1=+00001		SSLI 1=+00001	✓	
SDI IN-BIT DEPTH (SDI1)	AUTO			VXX: SBTI 1=+00000	QVX: SBTI 1	SBTI 1=+00000	✓	
	12-bit			VXX: SBTI 1=+00001		SBTI 1=+00001	✓	
	10-bit			VXX: SBTI 1=+00002		SBTI 1=+00002	✓	
SDI IN-3G SDI MAPPING (SDI1)	AUTO			VXX: SGM1 1=+00000	QVX: SGM1 1	SGM1 1=+00000	✓	
	LEVEL A			VXX: SGM1 1=+00001		SGM1 1=+00001	✓	
	LEVEL B			VXX: SGM1 1=+00002		SGM1 1=+00002	✓	
MULTI PROJECTOR SYNC - MODE	OFF			VXX: MPSI 1=+00000	QVX: MPSI 1	MPSI 1=+00000	✓	
	MASTER			VXX: MPSI 1=+00001		MPSI 1=+00001	✓	
	SLAVE			VXX: MPSI 1=+00002		MPSI 1=+00002	✓	
FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST	OFF			VXX: CSYI 1=+00000	QVX: CSYI 1	CSYI 1=+00000	✓	
	ON			VXX: CSYI 1=+00001		CSYI 1=+00001	✓	
MULTI PROJECTOR SYNC - SHUTTER SYNC.	OFF			VXX: SSYI 1=+00000	QVX: SSYI 1	SSYI 1=+00000	✓	
	ON			VXX: SSYI 1=+00001		SSYI 1=+00001	✓	
INPUT GUIDE	OFF			OI D: 0	QDI	0	✓	
	ON (SIMPLE)			OI D: 1		1	✓	
OSD POSITION	UPPER LEFT			ODP: 1	QDP	1	✓	
	CETRE LEFT			ODP: 2		2	✓	
	LOWER LEFT			ODP: 3		3	✓	
	TOP CENTER			ODP: 4		4	✓	
	CENTER			ODP: 5		5	✓	
	LOEER CENTER			ODP: 6		6	✓	
	UPPER RIGHT			ODP: 7		7	✓	
	CENTER RIGHT			ODP: 8		8	✓	
	LOWER RIGHT			ODP: 9		9	✓	
OSD ROTATION	OFF			VXX: OSRI 1=+00000	QVX: OSRI 1	OSRI 1=+00000	✓	
	CLOCKWISE			VXX: OSRI 1=+00001		OSRI 1=+00001	✓	
	COUNTER CLOCKWISE			VXX: OSRI 1=+00002		OSRI 1=+00002	✓	
OSD MEMORY	OFF			VXX: OMYI 0=+00000	QVX: OMYI 0	OMYI 0=+00000	✓	
	ON			VXX: OMYI 0=+00001		OMYI 0=+00001	✓	
ON SCREEN	OFF			OOS: 0	QOS	0	✓	
	ON			OOS: 1		1	✓	
WARNING MESSAGE	OFF			VXX: WMDI 0=+00000	QVX: WMDI 0	WMDI 0=+00000	✓	
	ON			VXX: WMDI 0=+00001		WMDI 0=+00001	✓	
OSD DESIGN	1(YELLOW)			MDD: 0	QOD	0	✓	
	2(BLUE)			MDD: 1		1	✓	
	3(WHITE)			MDD: 2		2	✓	
	4(GREEN)			MDD: 3		3	✓	
	5(PEACH)			MDD: 4		4	✓	
	6(BROWN)			MDD: 5		5	✓	
CLOSED CAPTION SETTING	OFF			OCC: 0	QCC	0	✓	
	CC1			OCC: 1		1	✓	
	CC2			OCC: 2		2	✓	
	CC3			OCC: 3		3	✓	
	CC4			OCC: 4		4	✓	
IMAGE ROTATION	OFF			VXX: I ROI 1=+00000	QVX: I ROI 1	I ROI 1=+00000	✓	
	CLOCKWISE			VXX: I ROI 1=+00001		I ROI 1=+00001	✓	
	COUNTER CLOCKWISE			VXX: I ROI 1=+00002		I ROI 1=+00002	✓	
SCREEN SETTING	16:10			VSF: 0	QSF	0	✓	
	16:9			VSF: 1		1	✓	
	4:3			VSF: 2		2	✓	
SCREEN POSITION-VERTICAL	min.			VXX: VSPI 0=- 00120	QVX: VSPI 0	VSPI 0=- 00120	-60	
	max.			VXX: VSPI 0=+00120		VSPI 0=+00120	60	
SCREEN POSITION-HOROZONTAL	min.			VXX: HSPI 0=- 00320	QVX: HSPI 0	HSPI 0=- 00320	-160	
	max.			VXX: HSPI 0=+00320		HSPI 0=+00320	+160	
STARTUP LOGO	OFF			ML0: 0	QLO	0	✓	
	USER LOGO			ML0: 1		1	✓	
	DEFAULT LOGO			ML0: 2		2	✓	
UNIFORMITY-PC CORRECTION *	OFF			VXX: UFM1 1=+00000	QVX: UFM1 1	UFM1 1=+00000	✓	
	ON			VXX: UFM1 1=+00001		UFM1 1=+00001	✓	
UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER			ESW: *, ***, ***, **	ESR: *, **	**, ***, ***, **	✓	
	* PARAMETER 1	WHITE		ESW: W, ***, ***, **	ESR: W, **	**, ***, ***, **	✓	
		RED		ESW: R, ***, ***, **	ESR: R, **	**, ***, ***, **	✓	
		GREEN		ESW: G, ***, ***, **	ESR: G, **	**, ***, ***, **	✓	
		BLUE		ESW: B, ***, ***, **	ESR: B, **	**, ***, ***, **	✓	
	* PARAMETER 2	VERTICAL(-127)		ESW: *, -127, ***, **	ESR: *, **	**, -127, ***, **	✓	
		VERTICAL(+127)		ESW: *, +127, ***, **	ESR: *, **	**, +127, ***, **	✓	
	* PARAMETER 3	HORIZONTAL(-127)		ESW: *, ***, -127, **	ESR: *, **	**, ***, -127, **	✓	
		HOROZONTAL(+127)		ESW: *, ***, +127, **	ESR: *, **	**, ***, +127, **	✓	
	* PARAMETER 4	L1(OFF)		ESW: *, ***, ***, 0*	ESR: *, 0*	0*, ***, ***, **	✓	
		L1(ON)		ESW: *, ***, ***, 1*	ESR: *, 1*	1*, ***, ***, **	✓	
		L2(OFF)		ESW: *, ***, ***, 0	ESR: *, 0	0*, ***, ***, **	✓	
		L2(ON)		ESW: *, ***, ***, 1	ESR: *, 1	1*, ***, ***, **	✓	
SHUTTER SETTING-FADE IN	0.0s(OFF)			VXX: SEFS1=0. 0	QVX: SEFS1	SEFS1=0. 0	✓	
	0.5s			VXX: SEFS1=0. 5		SEFS1=0. 5	✓	
	1.0s			VXX: SEFS1=1. 0		SEFS1=1. 0	✓	
	1.5s			VXX: SEFS1=1. 5		SEFS1=1. 5	✓	
	2.0s			VXX: SEFS1=2. 0		SEFS1=2. 0	✓	
	2.5s			VXX: SEFS1=2. 5		SEFS1=2. 5	✓	
	3.0s			VXX: SEFS1=3. 0		SEFS1=3. 0	✓	
	3.5s			VXX: SEFS1=3. 5		SEFS1=3. 5	✓	
	4.0s			VXX: SEFS1=4. 0		SEFS1=4. 0	✓	
	5.0s			VXX: SEFS1=5. 0		SEFS1=5. 0	✓	
	7.0s			VXX: SEFS1=7. 0		SEFS1=7. 0	✓	
	10.0s			VXX: SEFS1=10. 0		SEFS1=10. 0	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C
	SHUTTER SETTING-FADE OUT	0.0s(OFF)		VXX: SEFS2=0. 0	QVX: SEFS2	SEFS2=0. 0	✓
		0.5s		VXX: SEFS2=0. 5		SEFS2=0. 5	✓
		1.0s		VXX: SEFS2=1. 0		SEFS2=1. 0	✓
		1.5s		VXX: SEFS2=1. 5		SEFS2=1. 5	✓
		2.0s		VXX: SEFS2=2. 0		SEFS2=2. 0	✓
		2.5s		VXX: SEFS2=2. 5		SEFS2=2. 5	✓
		3.0s		VXX: SEFS2=3. 0		SEFS2=3. 0	✓
		3.5s		VXX: SEFS2=3. 5		SEFS2=3. 5	✓
		4.0s		VXX: SEFS2=4. 0		SEFS2=4. 0	✓
		5.0s		VXX: SEFS2=5. 0		SEFS2=5. 0	✓
	7.0s		VXX: SEFS2=7. 0		SEFS2=7. 0	✓	
	10.0s		VXX: SEFS2=10. 0		SEFS2=10. 0	✓	
	SHUTTER SETTING-STARTUP	OPEN		VXX: SEFI 3=+00000	QVX: SEFI 3	SEFI 3=+00000	✓
		CLOSE		VXX: SEFI 3=+00001		SEFI 3=+00001	✓
	BACK COLOR	BLUE		OBC: 0	QBC	0	✓
		BLACK		OBC: 1		1	✓
USER LOGO			OBC: 2		2	✓	
DEFAULT LOGO			OBC: 3		3	✓	
WAVEFORM MONITOR	OFF		OWM: 0	QWM	0	✓	
	LUMINANCE		OWM: 5		5	✓	
	RED		OWM: 6		6	✓	
	GREEN		OWM: 7		7	✓	
WAVEFORM MONITOR-LINE ADJ.	0		VXX: WMLI 0=+00000	QVX: WMLI 0	WMLI 0=+00000	✓	
	+2159		VXX: WMLI 0=+02159		WMLI 0=+02159	✓	
CUT OFF-RED	OFF		VXX: CUTI 1=+00000	QVX: CUTI 1	CUTI 1=+00000	✓	
	ON		VXX: CUTI 1=+00001		CUTI 1=+00001	✓	
CUT OFF-GREEN	OFF		VXX: CUTI 2=+00000	QVX: CUTI 2	CUTI 2=+00000	✓	
	ON		VXX: CUTI 2=+00001		CUTI 2=+00001	✓	
CUT OFF-BLUE	OFF		VXX: CUTI 3=+00000	QVX: CUTI 3	CUTI 3=+00000	✓	
	ON		VXX: CUTI 3=+00001		CUTI 3=+00001	✓	
PROJECTOR ID	0(ALL)		RIS: 00			✓	
	64		RIS: 64			✓	
ID ALL	OFF		RVS: 0	QVY	0	✓	
	ON		RVS: 1		1	✓	
PROJECTION METHOD INSTALLATION	FRONT/DESK		OIL: 0	QSP	0	✓	
	REAR/DESK		OIL: 1		1	✓	
	FRONT/CEILING		OIL: 2		2	✓	
	REAR/CEILING		OIL: 3		3	✓	
	FRONT/AUTO		OIL: 4		4	✓	
	REAR/AUTO		OIL: 5		5	✓	
PROJECTION METHOD(AUTO)	FRONT/DESK			QVX: PJMI 2	PJMI 2=+00000	✓	
	REAR/DESK				PJMI 2=+00001	✓	
	FRONT/CEILING				PJMI 2=+00002	✓	
	REAR/CEILING				PJMI 2=+00003	✓	
AUTO COOLING CONDITION-STATUS	FLOOR			QVX: ADRI 1	ADRI 1=+00000	✓	
	CEILING				ADRI 1=+00001	✓	
	VERTICAL UP				ADRI 1=+00002	✓	
	VERTICAL DOWN				ADRI 1=+00003	✓	
	PORTRAIT				ADRI 1=+00004	✓	
OPERATING MODE	NORMAL		VXX: OPEI 1=+00000	QVX: OPEI 1	OPEI 1=+00000	✓	
	ECO		VXX: OPEI 1=+00001		OPEI 1=+00001	✓	
	LONG LIFE1		VXX: OPEI 1=+00011		OPEI 1=+00011	✓	
	LONG LIFE2		VXX: OPEI 1=+00012		OPEI 1=+00012	✓	
	LONG LIFE3		VXX: OPEI 1=+00013		OPEI 1=+00013	✓	
	QUIET1		VXX: OPEI 1=+00021		OPEI 1=+00021	✓	
	QUIET2		VXX: OPEI 1=+00022		OPEI 1=+00022	✓	
	USER1(USER)		VXX: OPEI 1=+00101		OPEI 1=+00101	✓	
	USER2		VXX: OPEI 1=+00102		OPEI 1=+00102	✓	
USER3		VXX: OPEI 1=+00103		OPEI 1=+00103	✓		
LIGHT OUTPUT	min.		VXX: LOPI 2=+00100	QVX: LOPI 2	LOPI 2=+00100	✓	
	max.		VXX: LOPI 2=+01000		LOPI 2=+01000	✓	
MAX LIGHT OUTPUT	min.		VXX: LOPI 3=+00100	QVX: LOPI 3	LOPI 3=+00100	✓	
	max.		VXX: LOPI 3=+01000		LOPI 3=+01000	✓	
BRIGHTNESS CONTROL-SETUP-CALIBRATION TIME	OFF		VXX: BTMI 1=+00000	QVX: BTMI 1	BTMI 1=+00000	✓	
	00:01		VXX: BTMI 1=+00001		BTMI 1=+00001	✓	
	23:59		VXX: BTMI 1=+02359		BTMI 1=+02359	✓	
	00:00		VXX: BTMI 1=+02400		BTMI 1=+02400	✓	
BRIGHTNESS CONTROL-SETUP-CALIBRATION MESSAGE	OFF		VXX: BMGI 1=+00000	QVX: BMGI 1	BMGI 1=+00000	✓	
	ON		VXX: BMGI 1=+00001		BMGI 1=+00001	✓	
BRIGHTNESS CONTROL-SETUP-CONSTANT MODE	OFF		VXX: BCMI 0=+00000	QVX: BCMI 0	BCMI 0=+00000	✓	
	AUTO		VXX: BCMI 0=+00001		BCMI 0=+00001	✓	
	PC		VXX: BCMI 0=+00002		BCMI 0=+00002	✓	
BRIGHTNESS CONTROL-SETUP-LINK	OFF		VXX: BCLI 0=+00000	QVX: BCLI 0	BCLI 0=+00000	✓	
	GROUP A		VXX: BCLI 0=+00001		BCLI 0=+00001	✓	
	GROUP B		VXX: BCLI 0=+00002		BCLI 0=+00002	✓	
	GROUP C		VXX: BCLI 0=+00003		BCLI 0=+00003	✓	
	GROUP D		VXX: BCLI 0=+00004		BCLI 0=+00004	✓	
BRIGHTNESS CONTROL-SETUP APPLY	APPLY		VXX: BCSI 0=+00001			✓	
STANDBY MODE	NORMAL		VXX: STMI 0=+00000	QVX: STMI 0	STMI 0=+00000	✓	
	ECO		VXX: STMI 0=+00003		STMI 0=+00003	✓	
QUICK STARTUP	OFF		VXX: QSUI 1=+00000	QVX: QSUI 1	QSUI 1=+00000	✓	
	ON		VXX: QSUI 1=+00001		QSUI 1=+00001	✓	
QUICK STARTUP-VALID PERIOD	30MIN.		VXX: QSUI 2=+00030	QVX: QSUI 2	QSUI 2=+00030	✓	
	60MIN.		VXX: QSUI 2=+00060		QSUI 2=+00060	✓	
	90MIN.		VXX: QSUI 2=+00090		QSUI 2=+00090	✓	
SCHEDULE	OFF		VXX: SCHI 0=+00000	QVX: SCHI 0	SCHI 0=+00000	✓	
	ON		VXX: SCHI 0=+00001		SCHI 0=+00001	✓	
SCHEDULE-PROGRAM ASSIGN	OFF		VXX: SPGI *=+00000	QVX: SPGI *	SPGI *=+00000	✓	
	PROGRAM1		VXX: SPGI *=+00001		SPGI *=+00001	✓	
	PROGRAM2		VXX: SPGI *=+00002		SPGI *=+00002	✓	
	PROGRAM3		VXX: SPGI *=+00003		SPGI *=+00003	✓	
	PROGRAM4		VXX: SPGI *=+00004		SPGI *=+00004	✓	
	PROGRAM5		VXX: SPGI *=+00005		SPGI *=+00005	✓	
	PROGRAM6		VXX: SPGI *=+00006		SPGI *=+00006	✓	
	PROGRAM7		VXX: SPGI *=+00007		SPGI *=+00007	✓	
	* PARAMETER	SUN		VXX: SPGI 0=+0000*	QVX: SPGI 0	SPGI 0=+0000*	✓
		MON		VXX: SPGI 1=+0000*	QVX: SPGI 1	SPGI 1=+0000*	✓
TUE			VXX: SPGI 2=+0000*	QVX: SPGI 2	SPGI 2=+0000*	✓	
WED			VXX: SPGI 3=+0000*	QVX: SPGI 3	SPGI 3=+0000*	✓	
THU			VXX: SPGI 4=+0000*	QVX: SPGI 4	SPGI 4=+0000*	✓	
FRI			VXX: SPGI 5=+0000*	QVX: SPGI 5	SPGI 5=+0000*	✓	
	SAT		VXX: SPGI 6=+0000*	QVX: SPGI 6	SPGI 6=+0000*	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES	
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C	
PROJECTOR SETUP	SCHEDULE-COMMAND SETTING	COMMAND Del		VXX: SCCS**00****	QVX: SCCS**=**	SCCS**00****	✓	
		STANDBY		VXX: SCCS**10****		SCCS**10****	✓	
		POWER ON		VXX: SCCS**11****		SCCS**11****	✓	
		SHUTTER OPEN		VXX: SCCS**20****		SCCS**20****	✓	
		SHUTTER CLOSE		VXX: SCCS**21****		SCCS**21****	✓	
		RGB1 INPUT		VXX: SCCS**31****		SCCS**31****	✓	
		RGB2 INPUT		VXX: SCCS**32****		SCCS**32****	✓	
		DVI-D INPUT		VXX: SCCS**51****		SCCS**51****	✓	
		SDI1 INPUT		VXX: SCCS**52****		SCCS**52****	✓	
		HDMI1 INPUT		VXX: SCCS**53****		SCCS**53****	✓	
		NORMAL		VXX: SCCS**70****		SCCS**70****	✓	
		ECO		VXX: SCCS**71****		SCCS**71****	✓	
		LONG LIFE1		VXX: SCCS**72****		SCCS**72****	✓	
		LONG LIFE2		VXX: SCCS**73****		SCCS**73****	✓	
		LONG LIFE3		VXX: SCCS**74****		SCCS**74****	✓	
		USER1(USER)		VXX: SCCS**75****		SCCS**75****	✓	
		USER2		VXX: SCCS**76****		SCCS**76****	✓	
		USER3		VXX: SCCS**77****		SCCS**77****	✓	
		SILENT1		VXX: SCCS**7A****		SCCS**7A****	✓	
		SILENT2		VXX: SCCS**7B****		SCCS**7B****	✓	
		DIGITAL LINK		VXX: SCCS**B0****		SCCS**B0****	✓	
		INPUT 1		VXX: SCCS**B1****		SCCS**B1****	✓	
		INPUT 2		VXX: SCCS**B2****		SCCS**B2****	✓	
		INPUT 3		VXX: SCCS**B3****		SCCS**B3****	✓	
		INPUT 4		VXX: SCCS**B4****		SCCS**B4****	✓	
		INPUT 5		VXX: SCCS**B5****		SCCS**B5****	✓	
		INPUT 6		VXX: SCCS**B6****		SCCS**B6****	✓	
		INPUT 7		VXX: SCCS**B7****		SCCS**B7****	✓	
		INPUT 8		VXX: SCCS**B8****		SCCS**B8****	✓	
		INPUT 9		VXX: SCCS**B9****		SCCS**B9****	✓	
		INPUT 10		VXX: SCCS**BA****		SCCS**BA****	✓	
		P IN P/Multi Display OFF		VXX: SCCS**90****		SCCS**90****	✓	
		P IN P/Multi Display USER1		VXX: SCCS**91****		SCCS**91****	✓	
		P IN P/Multi Display USER2		VXX: SCCS**92****		SCCS**92****	✓	
		P IN P/Multi Display USER3		VXX: SCCS**93****		SCCS**93****	✓	
		QUICK STARTUP OFF		VXX: SCCS**A2****		SCCS**A2****	✓	
	QUICK STARTUP ON		VXX: SCCS**A3****		SCCS**A3****	✓		
		* PARAMETER1	PROGRAM1		VXX: SCCS1=*****	QVX: SCCS1=**	SCCS1=*****	✓
			PROGRAM2		VXX: SCCS2=*****	QVX: SCCS2=**	SCCS2=*****	✓
			PROGRAM3		VXX: SCCS3=*****	QVX: SCCS3=**	SCCS3=*****	✓
			PROGRAM4		VXX: SCCS4=*****	QVX: SCCS4=**	SCCS4=*****	✓
			PROGRAM5		VXX: SCCS5=*****	QVX: SCCS5=**	SCCS5=*****	✓
			PROGRAM6		VXX: SCCS6=*****	QVX: SCCS6=**	SCCS6=*****	✓
			PROGRAM7		VXX: SCCS7=*****	QVX: SCCS7=**	SCCS7=*****	✓
		* PARAMETER2	COMMAND 1		VXX: SCCS*01*****	QVX: SCCS*01	SCCS*01*****	✓
			COMMAND 16		VXX: SCCS*16*****	QVX: SCCS*16	SCCS*16*****	✓
		* PARAMETER3	00:00		VXX: SCCS*00000000		SCCS*00000000	✓
	23:59			VXX: SCCS*2359		SCCS*2359	✓	
	STARTUP INPUT SELECT	RGB1		VXX: SI SS1=RG1	QVX: SI SS1	SI SS1=RG1	✓	
		RGB2		VXX: SI SS1=RG2		SI SS1=RG2	✓	
		DVI-D		VXX: SI SS1=DVI		SI SS1=DVI	✓	
		HDMI1		VXX: SI SS1=HD1		SI SS1=HD1	✓	
		DIGITAL LINK		VXX: SI SS1=DL1		SI SS1=DL1	✓	
		SDI1		VXX: SI SS1=SD1		SI SS1=SD1	✓	
		LAST USED		VXX: SI SS1=LSU		SI SS1=LSU	✓	
		LAST USED		VXX: SI SI 2=+00000	QVX: SI SI 2	SI SI 2=+00000	✓	
	STARTUP INPUT SELECT (DIGITAL LINK)	INPUT1		VXX: SI SI 2=+00001		SI SI 2=+00001	✓	
		INPUT2		VXX: SI SI 2=+00002		SI SI 2=+00002	✓	
		INPUT3		VXX: SI SI 2=+00003		SI SI 2=+00003	✓	
		INPUT4		VXX: SI SI 2=+00004		SI SI 2=+00004	✓	
		INPUT5		VXX: SI SI 2=+00005		SI SI 2=+00005	✓	
		INPUT6		VXX: SI SI 2=+00006		SI SI 2=+00006	✓	
		INPUT7		VXX: SI SI 2=+00007		SI SI 2=+00007	✓	
		INPUT8		VXX: SI SI 2=+00008		SI SI 2=+00008	✓	
		INPUT9		VXX: SI SI 2=+00009		SI SI 2=+00009	✓	
		INPIT10		VXX: SI SI 2=+00010		SI SI 2=+00010	✓	
	RS232C-RESPONSE	OFF		RVS: 0	QVY	0	✓	
		ON		RVS: 1		1	✓	
	NO SIGNAL SHUT-OFF	DISABLE		OAF: 00	QAF	00	✓	
		10min		OAF: 10		10	✓	
		20min		OAF: 20		20	✓	
		30min		OAF: 30		30	✓	
		40min		OAF: 40		40	✓	
		50min		OAF: 50		50	✓	
		60min		OAF: 60		60	✓	
		70min		OAF: 70		70	✓	
		80min		OAF: 80		80	✓	
		90min		ODR: 90		90	✓	
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX: SLOI 1=+00000	QVX: SLOI 1	SLOI 1=+00000	✓	
		10SEC.		VXX: SLOI 1=+00010		SLOI 1=+00010	✓	
		20SEC.		VXX: SLOI 1=+00020		SLOI 1=+00020	✓	
		30SEC.		VXX: SLOI 1=+00030		SLOI 1=+00030	✓	
		1MIN.		VXX: SLOI 1=+00060		SLOI 1=+00060	✓	
		2MIN.		VXX: SLOI 1=+00120		SLOI 1=+00120	✓	
		3MIN.		VXX: SLOI 1=+00180		SLOI 1=+00180	✓	
		5MIN.		VXX: SLOI 1=+00300		SLOI 1=+00300	✓	
		DEFAULT		VXX: RMPI 0=+00000	QVX: RMPI 0	RMPI 0=+00000	✓	
	USER		VXX: RMPI 0=+00001		RMPI 0=+00001	✓		
	F/FW SERIES		VXX: RMPI 0=+00003		RMPI 0=+00003	✓		
	REMOTE2 - PIN2	NONE		VXX: RMPS1=P2<NONE	QVX: RMPS1=P2	RMPS1=P2<NONE	✓	
		POWER		VXX: RMPS1=P2<POWER		RMPS1=P2<POWER	✓	
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX: RMPS1=P*<****	QVX: RMPS1=P*		✓	
		* PARAMETER1	PIN3		VXX: RMPS1=P3<****		RMPS1=P3<****	✓
			PIN4		VXX: RMPS1=P4<****		RMPS1=P4<****	✓
			PIN5		VXX: RMPS1=P5<****		RMPS1=P5<****	✓
			PIN6		VXX: RMPS1=P6<****		RMPS1=P6<****	✓
		PIN7		VXX: RMPS1=P7<****		RMPS1=P7<****	✓	
		* PARAMETER2	NONE		VXX: RMPS1=P*<NONE		RMPS1=P*<NONE	✓
			RGB1		VXX: RMPS1=P*<RGB1		RMPS1=P*<RGB1	✓
	RGB2			VXX: RMPS1=P*<RGB2		RMPS1=P*<RGB2	✓	
	HDMI			VXX: RMPS1=P*<HDMI		RMPS1=P*<HDMI	✓	
	REMOTE2 - PIN8	HDMI1		VXX: RMPS1=P*<HDMI 1		RMPS1=P*<HDMI 1	✓	
		SDI1		VXX: RMPS1=P*<SD1		RMPS1=P*<SD1	✓	
	DIGITAL LINK		VXX: RMPS1=P*<DLINK		RMPS1=P*<DLINK	✓		
	FUNCTION BUTTON	NONE		VXX: RMPS1=P8<NONE	QVX: RMPS1=P8	RMPS1=P8<NONE	✓	
		SHUTTER	SHUTTER	VXX: RMPS1=P8<SHUTTER		RMPS1=P8<SHUTTER	✓	
	FUNCTION BUTTON	DISABLE		OFC: 0	QFC	0	✓	
		SYSTEM SELECTOR		OFC: 1		1	✓	
		SYSTEM DAYLIGHT VIEW		OFC: 2		2	✓	
		SUB MEMORY		OFC: 3		3	✓	
		FREEZE		OFC: 4		4	✓	
		P IN P		OFC: 5		5	✓	
		WAVEFORM MONITOR		OFC: 6		6	✓	
	PROJECTION METHOD		OFC: 10		10	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C
	DATE AND TIME-DATE SETTING	Year: yyyy		TSD: 201506151	QGD	201506161	✓
		Month: mm		TSD: <i>yyyymmddw</i>		<i>yyyymmddw</i>	✓
		Date: dd					✓
		Day:w(1~7:Mon~Sun)					✓
	DATE AND TIME-TIME SETTING	Hour: hh		TST: 154503	QGT	154503	✓
		Minute: mm		TST: <i>hhmmss</i>		<i>hhmmss</i>	✓
		Second: ss					✓
	DATE AND TIME-NTP SYNCHRONIZATION	OFF		VXX: NTPI0=+00000	QVX: NTPI0	NTPI0=+00000	✓
	LENS CALIBRATION	ON		VXX: NTPI0=+00001		NTPI0=+00001	✓
	INITIALIZE-ALL USER DATA	EXECUTE (ALL)		VXX: LNSI0=+00001			✓
		USER INITILIZE		VXX: RSTS1=0 <i>password</i>			✓
	INITIAL START UP	USER RESTORE		VXX: RSTS1=1 <i>password</i>			✓
		STANDBY		OPY: 0	QPY	0	✓
		ON		OPY: 1		1	✓
	MODEL NAME	LAST MEMORY		OPY: 2		2	✓
		MODEL NAME			QID	<i>MODELNAME</i>	✓
		SERIAL NUMBER	SW0101234		QSN	<i>SW0101234</i>	✓
	PROJECTOR RUNTIME	7864320H			QVX: RTMS1	RTMS1=7864320	✓
	LAMP1(LIGHT1) RUNTIME	9999H			QSL: 1	9999	✓
	LAMP2(LIGHT2) RUNTIME	9999H			QSL: 2	9999	✓
	LIGHT1 RUNTIME	7864320H			QVX: LRTS3=00	LRTS3=00: 7864320	✓
	LIGHT2 RUNTIME	7864320H			QVX: LRTS3=01	LRTS3=01: 7864320	✓
	LIGHT STATUS	ALL OFF			QLS	0	✓
		1:ON, 2:OFF				1	✓
		1:OFF, 2:ON				2	✓
		ALL ON				3	✓
	MAC ADDRESS	AB0102030405			QMA	<i>AB0102030405</i>	✓
	MAIN FIRMWARE VERSION	V1.00.01			QVX: SVRS0	SVRS0=1. 00. 01	✓
	SUB FIRMWARE VERSION	V1.00.01			QVX: SVRS2	SVRS2=1. 00. 01	✓
	INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)			QVX: NSGS1	NSGS1=*****.....	✓
		CHANNEL2 (SUB CH)			QVX: NSGS2	NSGS2=*****.....	✓
	TEMPERATURE (INTAKE)	0030/0080			QTM: 0	0030/0080	✓
TEMPERATURE (EXHAUST AIR)	0030/0080			QTM: 1	0030/0080	✓	
TEMPERATURE (OPTICS MODULE)	0030/0080			QTM: 2	0030/0080	✓	
TEMPERATURE (LIGHT1 / LIGHT1-P)	0030/0080			QTM: 11	0030/0080	✓	
TEMPERATURE (LIGHT2 / LIGHT1-P IN P-MODE)	0030/0080			QTM: 12	0030/0080	✓	
P IN P-MODE	OFF		OPP: 0	QPP	0	✓	
	USER1		OPP: 1		1	✓	
	USER2		OPP: 2		2	✓	
	USER3		OPP: 3		3	✓	
P IN P-MAIN WINDOW	RGB1		MSI: RG1	QIM	RG1	✓	
	RGB2		MSI: RG2		RG2	✓	
	DVI		MSI: DVI		DVI	✓	
	HDMI1		MSI: HD1		HD1	✓	
	SD1		MSI: SD1		SD1	✓	
P IN P-MAIN WINDOW-SIZE-INTERLOCKED	OFF		MSL: 0			✓	
	ON		MSL: 1			✓	
P IN P-MAIN WINDOW-SIZE-VERTICAL	10		MSV: 010			✓	
	100		MSV: 100			✓	
P IN P-MAIN WINDOW-SIZE-HORIZONTAL	10		MSH: 010			✓	
	100		MSH: 100			✓	
P IN P-MAIN WINDOW-SIZE-BOTH	10		MSZ: 010			✓	
	100		MSZ: 100			✓	
P IN P-MAIN WINDOW-POSITION-VERTICAL	<i>min.</i>		MPV: - 600			-600	
	<i>max.</i>		MPV: +600			+600	
P IN P-MAIN WINDOW-POSITION-HORIZONTAL	<i>min.</i>		MPH: - 960			-960	
	<i>max.</i>		MPH: +960			+960	
P IN P-MAIN WINDOW-SIZE	INTERLOCKED	OFF		QSM	OF. V010. H010. HV100	✓	
		ON			ON. V010. H010. HV100	✓	
	VERTICAL SIZE	10-100			** , V010. H*** , HV***	✓	
	HORIZONTAL SIZE	10-100			** , V*** , H010. HV***	✓	
	H/V SIZE	10-100			** , V*** , H*** , HV100	✓	
P IN P-MAIN WINDOW-POSITION	V:-364 +364			QPA	V- 364. H- 651	✓	
	H:-651 +651				V+364. H+651	✓	
P IN P-SUB WINDOW	RGB1		SIS: RG1	QIS	RG1	✓	
	RGB2		SIS: RG2		RG2	✓	
	DVI		SIS: DVI		DVI	✓	
	HDMI1		SIS: HD1		HD1	✓	
	SD1		SIS: SD1		SD1	✓	
P IN P-SUB WINDOW-SIZE	INTERLOCKED	OFF		QSS	OF. V010. H010. HV100	✓	
		ON			ON. V010. H010. HV100	✓	
	VERTICAL SIZE	10-100			** , V010. H*** , HV***	✓	
	HORIZONTAL SIZE	10-100			** , V*** , H010. HV***	✓	
	H/V SIZE	10-100			** , V*** , H*** , HV100	✓	
P IN P-SUB WINDOW-POSITION	V:-364 +364			QPS	V- 364. H- 651	✓	
	H:-651 +651				V+364. H+651	✓	
P IN P-SUB WINDOW-SIZE-INTERLOCKED	OFF		SSL: 0		0	✓	
	ON		SSL: 1		1	✓	
P IN P-SUB WINDOW-SIZE-VERTICAL	10		SSV: 010		010	✓	
	100		SSV: 100		100	✓	
P IN P-SUB WINDOW-SIZE-HORIZONTAL	10		SSH: 010		010	✓	
	100		SSH: 100		100	✓	
P IN P-SUB WINDOW-SIZE-BOTH	10		SSZ: 010		010	✓	
	100		SSZ: 100		100	✓	
P IN P-SUB WINDOW-POSITION-VERTICAL	-600		SPV: - 600		- 600	-600	
	+600		SPV: +600		+600	+600	
P IN P-SUB WINDOW-POSITION-HORIZONTAL	-960		SPH: - 960		- 960	-960	
	+960		SPH: +960		+960	+960	
P IN P-SUB WINDOW-CLOCK PHASE	0		VXX: SCPI0=+00000	QVX: SCPI0	SCPI0=+00000	✓	
	31		VXX: SCPI0=+00031		SCPI0=+00031	✓	
P IN P-FRAME LOCK	MAIN WINDOW		PFL: 0	QPF	0	✓	
	SUB WINDOW		PFL: 1		1	✓	
P IN P-TYPE	MAIN WINDOW		PTP: 0	QPT	0	✓	
	SUB WINDOW		PTP: 1		1	✓	
TEST PATTERN	TEST PATTERN	Off	OTS: 00	QTS	00	✓	
		White	OTS: 01		01	✓	
		Black	OTS: 02		02	✓	
		Window	OTS: 05		05	✓	
		Reversed Window	OTS: 06		06	✓	
		Color Bar V	OTS: 08		08	✓	
		Convergence	OTS: 11		11	✓	
		Color Bar Side	OTS: 51		51	✓	
		16:9/4:3	OTS: 59		59	✓	
		Focus Red	OTS: 70		70	✓	
		Focus Green	OTS: 71		71	✓	
		Focus Blue	OTS: 72		72	✓	
	Focus Cyan	OTS: 73		73	✓		
	Focus Magenta	OTS: 74		74	✓		
	Focus Yellow	OTS: 75		75	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ870 SERIES
				COMMANDS	COMMANDS	CALL BACK	RZ870 FRZ88C
SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM			✓
	SIGNAL LIST-DELETE	A1		ODM A1			✓
		A2		ODM A2			✓
		A7		ODM A7			✓
		A8		ODM A8			✓
		L1		ODM L1			✓
		L2		ODM L2			✓
		L7		ODM L7			✓
		L8		ODM L8			✓
	SUB MEMORY LIST-CHANGEOVER	01		OCS: 01			✓
		96		OCS: 96			✓
	SUB MEMORY LIST-CHANGEOVER (EXTENDED)	01		OCS: 01- 01			✓
		96		OCS: 95- 96			✓
	SUB MEMORY LIST-REGISTRATION			OES			✓
SUB MEMORY LIST-DELETE	01		ODS: 01- 01			✓	
	96		ODS: 95- 96			✓	
SUB MEMORY USAGE STATE	01			QSB	01	✓	
	96				96	✓	
SECURITY	SECURITY SETTING	OFF			QVX: SPWI 1	SPWI 1=+00000	✓
		ON				SPWI 1=+00001	✓
NETWORK	DIGITAL LINK MODE	AUTO		VXX: DKMI 1=+00001	QVX: DKMI 1	DKMI 1=+00001	✓
		DIGITAL LINK		VXX: DKMI 1=+00002		DKMI 1=+00002	✓
		ETHERNET		VXX: DKMI 1=+00003		DKMI 1=+00003	✓
		LONG REACH MODE		VXX: DKMI 1=+00004		DKMI 1=+00004	✓
	DIGITAL LINK-DUPLEX(Ethernet)	Auto negotiation		VXX: DKDI 1=+00000	QVX: DKDI 1	DKDI 1=+00000	✓
		100BaseTX-Full		VXX: DKDI 1=+00001		DKDI 1=+00001	✓
		100BaseTX-Half		VXX: DKDI 1=+00002		DKDI 1=+00002	✓
	DIGITAL LINK-DUPLEX(DIGITAL LINK)	Auto negotiation		VXX: DKDI 2=+00000	QVX: DKDI 2	DKDI 2=+00000	✓
		100BaseTX-Full		VXX: DKDI 2=+00001		DKDI 2=+00001	✓
		100BaseTX-Half		VXX: DKDI 2=+00002		DKDI 2=+00002	✓
	DIGITAL LINK STATUS-LINK	NO LINK			QVX: DKSI 1	DKSI 1=+00000	✓
		DIGITAL LINK				DKSI 1=+00001	✓
		LPM				DKSI 1=+00002	✓
		ETHERNET				DKSI 1=+00003	✓
	DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX: DKSI 2	DKSI 2=+00000	✓
		OFF				DKSI 2=+00001	✓
		ON				DKSI 2=+00002	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX: DKSI 3	DKSI 3=- 00255	✓
	DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	0				DKSI 3=+00000	✓
		-255			QVX: DKSI 4	DKSI 4=- 00255	✓
		0				DKSI 4=+00000	✓
	DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2...			QVX: DL1S1	DL1S1=HD1: HDMI 1, ****: ***	✓
	PROJECTOR NAME SETTING	PROJECTOR1		VXX: NCGS8=PROJECTOR1	QVX: NCGS8	NCGS8=PROJECTOR1	✓
	Art-Net SETUP	OFF		VXX: DANI 1=+00000	QVX: DANI 1	DANI 1=+00000	✓
ON(2.*.*)			VXX: DANI 1=+00002		DANI 1=+00002	✓	
ON(10.*.*)			VXX: DANI 1=+00003		DANI 1=+00003	✓	
ON(MANUAL)			VXX: DANI 1=+00004		DANI 1=+00004	✓	
Art-Net SETUP-START ADDRESS	1		VXX: DANI 3=+00001	QVX: DANI 3	DANI 3=+00001	✓	
	501		VXX: DANI 3=+00501		DANI 3=+00501	✓	
Art-Net SETUP-NET	0		VXX: DANI 4=+00000	QVX: DANI 4	DANI 4=+00000	✓	
	127		VXX: DANI 4=+00127		DANI 4=+00127	✓	
Art-Net SETUP-SUB NET	0		VXX: DANI 5=+00000	QVX: DANI 5	DANI 5=+00000	✓	
	15		VXX: DANI 5=+00015		DANI 5=+00015	✓	
Art-Net SETUP-UNIVERS	0		VXX: DANI 6=+00000	QVX: DANI 6	DANI 6=+00000	✓	
	15		VXX: DANI 6=+00015		DANI 6=+00015	✓	
Art-Net	OFF		VXX: DANI 7=+00000	QVX: DANI 7	DANI 7=+00000	✓	
	WIRELESS LAN		VXX: DANI 7=+00011		DANI 7=+00011	✓	
Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX: DANI 8=+00000	QVX: DANI 8	DANI 8=+00000	✓	
	1		VXX: DANI 8=+00001		DANI 8=+00001	✓	
	USER		VXX: DANI 8=+00100		DANI 8=+00100	✓	
MIRRORING	MODERATOR		VXX: MI RI 1=+00001	QVX: MI RI 1	MI RI 1=+00001	✓	
	MULTI		VXX: MI RI 1=+00002		MI RI 1=+00002	✓	
	SINGLE		VXX: MI RI 1=+00004		MI RI 1=+00004	✓	

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.