

	Function	WV-SFV781L/SPV781L	WV-SPN611/SPN631	WV-SPW631LT/SPW631L	WV-SFN611L/SFN631L/SFR611L/SFR631L/SFV611L/SFV631L/SFV631LT	WV-SPW611L/SPW611	WV-SPN531	WV-SFN531/SFR531/SFV531	WV-SW598/SC588
WJ-NV300 (V1.30) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes
	Audio *8	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	yes
WJ-NV200 (V2.30) *14	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	-	yes	yes	yes	[SFN611L]	yes	[SFN631L]	yes
	MPEG4	-	-	-	-	-	-	-	-
	H.264	-	yes*12	yes*12	yes*12	[SFN611L]*12	yes*12	[SFN631L]	yes
	Audio *8	-	yes	yes	yes	[SFN611L]	yes	[SFN631L]	yes
WJ-ND400K (V5.00) *14	PTZ	-	-	-	-	-	-	-	yes
	Motion detection (VMD)	-	yes	yes	yes	[SFN611L]	yes	[SFN631L]	yes
	MJPEG	yes	yes	yes	yes	[SFN611L]	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	[SFN611L]	yes	yes	yes
WJ-ND300A (V5.20) *4, *14	Audio *8	yes	yes	yes	yes	[SFN611L]	yes	yes	yes
	PTZ	-	-	-	-	-	-	-	yes
	Motion detection (VMD)	yes	yes	yes	yes	[SFN611L]	yes	yes	yes
	MJPEG	[SF335] *2	[SP305] *2	[SP305] *2	[SF335]*2	[SP305]	[SP305] *2	[SF335]*2	[SC385]*2
	MPEG4	-	-	-	-	-	-	-	-
WJ-ND200 (V3.35) *4, *14	H.264	-	-	-	-	-	-	-	-
	Audio	-	-	-	-	-	-	-	-
	PTZ	-	-	-	-	-	-	-	[SC385]
	Motion detection (VMD)	-	-	-	-	-	-	-	-
	MJPEG	[SF335] *2	[SP305] *2	[SP305] *2	[SF335]*2	[SP305]	[SP305] *2	[SF335]*2	[SC385]*2
WJ-ND200 (V3.35) *4, *14	MPEG4	-	-	-	-	-	-	-	-
	H.264	-	-	-	-	-	-	-	-
	Audio *8*11	[SF335]	[SP305]	[SP305]	[SF335]	[SP305]	[SP305]	[SF335]	[SC385]
	PTZ	-	-	-	-	-	-	-	[SC385]
	Motion detection (VMD)	-	-	-	-	-	-	-	-

[substitute model] : Register as a substitute model.

*1 : Only for remote PTZ cameras.

*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.

*3 : Each recorder supports only wireline connection.

*4 : Displaying 16:9 is not supported on a NDR browser.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726 and 32kbps.

*11 : This function is supported only when playing back.

*12 : Supported up to 30 ips

*13 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.

*14 :Streams of H.264(3) and H.264(4) are not supported

*15 :When using over 6Mbps for bitrate, please use the firmware version 4.59. SFV481,SFN480 support will be only 1-8ch.

	Function	WV-SW559/SF549/SF539	WV-SW558/SF548/SF538	WV-SP509	WV-SP508	WV-NW502S/NP502	WV-SFV481/SFN480 *7	WV-SW458/SF438/SF448E *7	WV-SPN310/SPN311
WJ-NV300 (V1.30) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes
	Audio *8	yes	-	yes	-	yes	yes	yes	yes
	PTZ	-	-	-	-	-	yes	yes	-
WJ-NV200 (V2.30) *14	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	no*13	yes	yes
	MPEG4	-	-	-	-	yes	-	-	-
	H.264	yes	yes	yes	yes	yes	no*13	yes	yes*12
	Audio *8	yes	-	yes	-	yes	no*13	yes	yes
WJ-ND400K (V5.00) *14	PTZ	-	-	-	-	-	-	yes	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	no*13	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes*15	yes	yes
	MPEG4	-	-	-	-	yes	-	-	-
	H.264	yes	yes	yes	yes	yes	yes*15	yes	yes
WJ-ND300A (V5.20) *4, *14	Audio *8	yes	-	yes	-	yes	yes*15	yes	yes
	PTZ	-	-	-	-	-	yes*15	yes	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes*15	yes	yes
	MJPEG	[SF335] *2	[SP102] *2	[SP305] *2	[SP102] *2	yes *2	-	-	[SP305]
	MPEG4	-	-	-	-	yes	-	-	-
WJ-ND200 (V3.35) *4, *14	H.264	-	-	-	-	yes	-	-	-
	Audio	-	-	-	-	-	-	-	-
	PTZ	-	-	-	-	-	-	-	-
	Motion detection (VMD)	-	-	-	-	-	-	-	-
	MJPEG	[SF335] *2	[SF335] *2	[SP305] *2	[SP305] *2	yes *2	-	-	[SP305]
WJ-ND200 (V3.35) *4, *14	MPEG4	-	-	-	-	yes	-	-	-
	H.264	-	-	-	-	yes	-	-	-
	Audio *8*11	[SF335]	-	[SP305]	-	yes	-	-	[SP305]
	PTZ	-	-	-	-	-	-	-	-
	Motion detection (VMD)	-	-	-	-	-	-	-	-

[substitute model] : Register as a substitute model.

*1 : Only for remote PTZ cameras.

*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.

*3 : Each recorder supports only wireline connection.

*4 : Displaying 16:9 is not supported on a NDR browser.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726 and 32kbps.

*11 : This function is supported only when playing back.

*12 : Supported up to 30 ips

*13 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.

*14 :Streams of H.264(3) and H.264(4) are not supported

*15 :When using over 6Mbps for bitrate, please use the firmware version 4.59. SFV481,SFN480 support will be only 1-8ch.

	Function	WV-SPW311LH	WV-SFN311/SFN310/ SFN311L/ SFR311/SFR310/ SFV311/SFV310	WV-SW397/SW397A	WV-SC387	WV-SW396/SW395/ SC386/SC384	WV-SC385	WV-SW355/SW352/ SF346/SF342	WV-SF330 series SP300 series
WJ-NV300 (V1.30) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes
	Audio *8	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	yes	yes	yes	yes	-	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes
WJ-NV200 (V2.30) *14	MJPEG	[SFN310]	yes	[SW598]	[SC588]	yes	yes	yes	yes
	MPEG4	-	-	-	-	yes	yes	yes	yes
	H.264	[SFN310]*12	yes*12	[SW598]	[SC588]	yes	yes	yes	yes
	Audio *8	[SFN310]	yes	[SW598]	[SC588]	yes	yes	yes	yes
	PTZ	-	-	[SW598]	[SC588]	yes	yes	-	-
	Motion detection (VMD)	[SFN310]	yes	[SW598]	[SC588]	yes	yes	yes	yes
WJ-ND400K (V5.00) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	yes	yes	yes	yes
	H.264	yes	yes	yes	yes	yes	yes	yes	yes
	Audio *8	yes	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	yes	yes	yes	yes	-	-
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes
WJ-ND300A (V5.20) *4, *14	MJPEG	[SP305]	[SF335]	[SC385]	[SC385]	[SC385]	yes	[SF335]	yes
	MPEG4	-	-	-	-	[SC385]	yes	[SF335]	yes
	H.264	-	-	-	-	[SC385]	yes	[SF335]	yes
	Audio	-	-	-	-	-	-	-	-
	PTZ	-	-	[SC385]	[SC385]	[SC385]	yes	-	-
	Motion detection (VMD)	-	-	-	-	-	-	-	-
WJ-ND200 (V3.35) *4, *14	MJPEG	[SP305]	[SF335]	[SC385]	[SC385]	[SC385]	yes	[SF335]	yes
	MPEG4	-	-	-	-	[SC385]	yes	[SF335]	yes
	H.264	-	-	-	-	[SC385]	yes	[SF335]	yes
	Audio *8*11	[SP305]	[SF335]	[SC385]	[SC385]	[SC385]	yes	[SF335]	yes
	PTZ	-	-	[SC385]	[SC385]	[SC385]	yes	-	-
	Motion detection (VMD)	-	-	-	-	-	-	-	-

[substitute model] : Register as a substitute model.

*1 : Only for remote PTZ cameras.

*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.

*3 : Each recorder supports only wireline connection.

*4 : Displaying 16:9 is not supported on a NDR browser.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726 and 32kbps.

*11 : This function is supported only when playing back.

*12 : Supported up to 30 ips

*13 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.

*14 :Streams of H.264(3) and H.264(4) are not supported

*15 :When using over 6Mbps for bitrate, please use the firmware version 4.59. SFV481,SFN480 support will be only 1-8ch.

	Function	WV-SW316L/SW316	WV-SW314	WV-SW158/SF138	WV-SW155/SW152/SW115	WV-SF135/SF132	WV-SP105/SP102	WV-SW175/SW172/ST165/ST162	WV-SW174W *3
WJ-NV300 (V1.30) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes
	Audio *8	yes	-	yes	-	-	-	yes	yes
	PTZ	-	-	-	-	-	-	yes	yes
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes
WJ-NV200 (V2.30) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	yes	yes	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes
	Audio *8	yes	-	yes	-	-	-	yes	yes
	PTZ	-	-	-	-	-	-	yes	yes
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes
WJ-ND400K (V5.00) *14	MJPEG	yes	yes	yes	yes	yes	yes	yes	yes
	MPEG4	yes	yes	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes	yes
	Audio *8	yes	-	yes	-	-	-	yes	yes
	PTZ	-	-	-	-	-	-	yes	yes
	Motion detection (VMD)	yes	yes	yes	yes	yes	yes	yes	yes
WJ-ND300A (V5.20) *4, *14	MJPEG	[SP305]	[SP102]	[SF335] *2	[SF335]	[SP102]	yes	[SC385]	[SC385]
	MPEG4	[SP305]	[SP305]	-	-	-	-	-	-
	H.264	[SP305]	[SP305]	-	[SF335]	[SF335]	yes	[SC385]	[SC385]
	Audio	-	-	-	-	-	-	-	-
	PTZ	-	-	-	-	-	-	[SC385]	[SC385]
	Motion detection (VMD)	-	-	-	-	-	-	-	-
WJ-ND200 (V3.35) *4, *14	MJPEG	[SP305]	[SP305]	[SF335] *2	[SF335]	[SF335]	yes	[SC385]	[SC385]
	MPEG4	[SP305]	[SP305]	-	-	-	-	-	-
	H.264	[SP305]	[SP305]	-	[SF335]	[SF335]	yes	[SC385]	[SC385]
	Audio *8*11	[SP305]	-	[SF335]	-	-	-	[SC385]	[SC385]
	PTZ	-	-	-	-	-	-	[SC385]	[SC385]
	Motion detection (VMD)	-	-	-	-	-	-	-	-

[substitute model] : Register as a substitute model.

*1 : Only for remote PTZ cameras.

*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.

*3 : Each recorder supports only wireline connection.

*4 : Displaying 16:9 is not supported on a NDR browser.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726 and 32kbps.

*11 : This function is supported only when playing back.

*12 : Supported up to 30 ips

*13 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.

*14 :Streams of H.264(3) and H.264(4) are not supported

*15 :When using over 6Mbps for bitrate, please use the firmware version 4.59. SFV481,SFN480 support will be only 1-8ch.

	Function	BB-HCM7 series	BB-HCM5 series	WJ-GxE500	WJ-GxE100
WJ-NV300 (V1.30) *14	MJPEG	yes	yes	yes	yes
	MPEG4	-	-	-	-
	H.264	yes	-	yes	yes
	Audio *8	yes	-	yes (ch1)	-
	PTZ	yes *1	yes *1	yes	yes
	Motion detection (VMD)	-	-	yes	yes
WJ-NV200 (V2.30) *14	MJPEG	yes	yes	yes	yes
	MPEG4	yes	-	yes	-
	H.264	yes	-	yes	yes
	Audio *8	yes	-	yes (ch1)	-
	PTZ	yes *1	yes *1	yes	yes
	Motion detection (VMD)	-	-	yes	yes
WJ-ND400K (V5.00) *14	MJPEG	yes	yes	yes	yes
	MPEG4	yes	-	yes	-
	H.264	yes	-	yes	yes
	Audio *8	yes	-	yes (ch1)	-
	PTZ	yes *1	yes *1	yes	yes
	Motion detection (VMD)	-	-	yes	yes
WJ-ND300A (V5.20) *4, *14	MJPEG	yes	yes	yes	[GXE500 ch1]
	MPEG4	yes	-	yes	-
	H.264	yes	-	yes	[GXE500 ch1]
	Audio	-	-	-	-
	PTZ	yes *1	yes *1	yes	[GXE500 ch1]
	Motion detection (VMD)	-	-	-	-
WJ-ND200 (V3.35) *4, *14	MJPEG	yes	yes	yes	[GXE500 ch1]
	MPEG4	yes	-	yes	-
	H.264	yes	-	yes	[GXE500 ch1]
	Audio *8*11	yes	-	yes (ch1)	-
	PTZ	yes *1	yes *1	yes	[GXE500 ch1]
	Motion detection (VMD)	-	-	-	-

[substitute model] : Register as a substitute model.

*1 : Only for remote PTZ cameras.

*2 : Support less than 1920x1080 ,including 1600x1200. 1920x1080 and 1600x1200 are not supported SD memory card backup and can be set the image quality:5-9 and the frame rate:up to 5fps.

*3 : Each recorder supports only wireline connection.

*4 : Displaying 16:9 is not supported on a NDR browser.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726 and 32kbps.

*11 : This function is supported only when playing back.

*12 : Supported up to 30 ips

*13 : When using WV-SFV481/WV-SFN480 with WJ-NV200, recording stops for about 10 seconds at the time of a screen change in a main monitor.

*14 :Streams of H.264(3) and H.264(4) are not supported

*15 :When using over 6Mbps for bitrate, please use the firmware version 4.59. SFV481,SFN480 support will be only 1-8ch.

	Function	WV-SFV781L/SPV781L	WV-SPN611/SPN631	WV-SPW631LT/SPW631L	WV-SFN611L/SFN631L/SFR611L/SFR631L/SFV611L/SFV631L/SFV631LT	WV-SPW611L/SPW611	WV-SPN531	WV-SFN531/SFR531/SFV531
WV-ASM200 (V4.00) Direct connection to camera	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-
WV-ASM100 (Ver8.00) *5, *14 Direct connection to camera	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	yes	yes	yes	yes	yes
WV-ASC970 (Ver14.00) Direct connection to camera	PTZ	-	-	-	-	-	-	-
	RTP over HTTP	-	-	-	-	-	-	-
	MJPEG	yes	yes	yes	yes	[SFN611L]	yes	yes
	MPEG4	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	[SFN611L]	yes	yes
WJ-GXD400 (Ver2.21) *6, *14	Audio*8	yes	yes	yes	yes	[SFN611L]	yes	yes
	PTZ	-	-	-	-	-	-	-
	RTP over HTTP	yes	yes	yes	yes	[SFN611L]	yes	yes
	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	-	-
BB-HNP17 (Ver4.05)	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*9	yes	yes	yes	yes	yes	yes	yes
	PTZ	-	-	-	-	-	-	-
	RTP over HTTP	-	-	-	-	-	-	-
	MJPEG	-	yes	yes	yes	yes	yes	yes
MPEG4	-	-	-	-	-	-	-	
H.264	-	yes	yes	yes	yes	yes	yes	
Audio*8	-	yes	yes	yes	yes	yes	yes	
PTZ	-	-	-	-	-	-	-	
RTP over HTTP	-	yes	yes	yes	yes	yes	yes	

- *1 : Only for remote PTZ cameras.
- *5 : WV-ASM100 does not support displaying 16:9.
- *6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA.
- *7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.
- *8 : Supported G.726.
- *9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.
- *14 : Streams of H.264(3) and H.264(4) are not supported.
- *16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.

	Function	WV-SW598/SC588	WV-SW559/SF549/SF539/SP509	WV-SW558/SF548/SF538/SP508	WV-NW502S/NP502	WV-SFV481/SFN480 *7	WV-SW458/SF438/SF448E *7	WV-SPN310/SPN311/SPW311LH
WV-ASM200 (V4.00) Direct connection to camera	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	yes	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	-	yes	yes	yes	yes
	PTZ	yes	-	-	-	yes	yes	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	yes
WV-ASM100 (Ver8.00) *5, *14 Direct connection to camera	MJPEG	yes	yes	yes	yes	-	-	yes
	MPEG4	-	-	-	yes	-	-	-
	H.264	yes	yes	yes	yes	-	-	yes
	Audio*8	yes	yes	-	yes	-	-	yes
	PTZ	yes	-	-	-	-	-	-
	RTP over HTTP	-	-	-	-	-	-	-
WV-ASC970 (Ver14.00) Direct connection to camera	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	yes	-	-	-
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	-	yes	yes	yes	yes
	PTZ	yes	-	-	-	yes	yes	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	yes
WJ-GXD400 (Ver2.21) *6, *14	MJPEG	yes	yes	yes	yes	-	-	yes
	MPEG4	-	-	-	yes	-	-	-
	H.264	yes	yes	yes	yes	-	-	yes
	Audio*9	yes	yes	-	yes	-	-	yes
	PTZ	-	-	-	-	-	-	-
	RTP over HTTP	-	-	-	-	-	-	-
BB-HNP17 (Ver4.05)	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	yes	-	-	-
	H.264	yes	yes	yes	yes	yes*16	yes	yes
	Audio*8	yes	yes	-	yes	yes	yes	yes
	PTZ	yes	-	-	-	yes	yes	-
	RTP over HTTP	yes	yes	yes	yes	yes	yes	yes

*1 : Only for remote PTZ cameras.

*5 : WV-ASM100 does not support displaying 16:9.

*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726.

*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.

*14 : Streams of H.264(3) and H.264(4) are not supported.

*16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.

	Function	WV-SFN311/SFN310/ SFN311L/ SFR311/SFR310/ SFV311/SFV310	WV-SW397/SW397A/ SC387	WV-SW396/SW395/ SC386/SC385/ SC384	WV-SW355/SW352/ SF346/SF342	WV-SF330 series SP300 series	WV-SW316L/SW316	WV-SW314
WV-ASM200 (V4.00) Direct connection to camera	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	yes	yes	yes	yes	yes
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	yes	yes	yes	yes	-
	PTZ	-	yes	yes	-	-	-	-
RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	yes
WV-ASM100 (Ver8.00) *5, *14 Direct connection to camera	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	yes	yes	yes	yes	yes
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	yes	yes	yes	yes	-
	PTZ	-	yes	yes	-	-	-	-
RTP over HTTP	-	-	-	-	-	-	-	
WV-ASC970 (Ver14.00) Direct connection to camera	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	yes	yes	yes	yes	yes
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	yes	yes	yes	yes	-
	PTZ	-	yes	yes	-	-	-	-
RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	
WJ-GXD400 (Ver2.21) *6, *14	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	yes	yes	yes	yes	yes
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*9	yes	yes	yes	yes	yes	yes	-
	PTZ	-	-	-	-	-	-	-
RTP over HTTP	-	-	-	-	-	-	-	
BB-HNP17 (Ver4.05)	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	yes	yes	yes	yes	yes
	H.264	yes	yes	yes	yes	yes	yes	yes
	Audio*8	yes	yes	yes	yes	yes	yes	-
	PTZ	-	yes	yes	-	-	-	-
RTP over HTTP	yes	yes	yes	yes	yes	yes	yes	

*1 : Only for remote PTZ cameras.

*5 : WV-ASM100 does not support displaying 16:9.

*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726.

*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.

*14 : Streams of H.264(3) and H.264(4) are not supported.

*16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.

	Function	WV-SW158/SF138	WV-SW155/SW152/SF135/SF132/SW115	WV-SP105/SP102	WV-SW175/SW172/ST165/ST162	WV-SW174W	BB-HCM7 series	BB-HCM5 series
WV-ASM200 (V4.00) Direct connection to camera	MJPEG	yes	yes	yes	yes	yes	-	-
	MPEG4	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	-	-
	Audio*8	yes	-	-	yes	yes	-	-
	PTZ	-	-	-	yes	yes	-	-
WV-ASM100 (Ver8.00) *5, *14 Direct connection to camera	RTP over HTTP	yes	yes	yes	yes	yes	-	-
	MJPEG	yes	yes	yes	yes	yes	-	-
	MPEG4	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	-	-
	Audio*8	yes	-	-	yes	yes	-	-
WV-ASC970 (Ver14.00) Direct connection to camera	PTZ	-	-	-	yes	yes	-	-
	RTP over HTTP	yes	yes	yes	yes	yes	-	-
	MJPEG	yes	yes	yes	yes	yes	-	-
	MPEG4	-	-	-	-	-	-	-
	H.264	yes	yes	yes	yes	yes	-	-
WJ-GXD400 (Ver2.21) *6, *14	Audio*8	yes	-	-	yes	yes	-	-
	PTZ	-	-	-	yes *9	yes *9	-	-
	RTP over HTTP	-	-	-	-	-	-	-
	MJPEG	yes	yes	yes	yes	yes	yes	yes
	MPEG4	-	-	-	-	-	yes	yes
BB-HNP17 (Ver4.05)	H.264	yes	yes	yes	yes	yes	yes	-
	Audio*8	yes	-	-	yes	yes	yes	yes
	PTZ	-	-	-	yes	yes	yes *1	yes *1
	RTP over HTTP	yes	yes	yes	yes	yes	-	-

- *1 : Only for remote PTZ cameras.
- *5 : WV-ASM100 does not support displaying 16:9.
- *6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA.
- *7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.
- *8 : Supported G.726.
- *9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.
- *14 : Streams of H.264(3) and H.264(4) are not supported.
- *16 : When displaying H.264 streaming of 2992x2992 resolution, please use a 64 bit OS and 4GB or more memory.

	Function	WJ-GXE500	WJ-GXE100	
WV-ASM200 (V4.00)	MJPEG	yes	yes	
	MPEG4	yes	-	
	H.264	yes	yes	
	Audio*8	yes (ch1)	-	
	PTZ	yes	yes	
Direct connection to camera	RTP over HTTP	yes	yes	
	WV-ASM100 (Ver8.00)	MJPEG	yes	-
		MPEG4	yes	-
		H.264	yes	-
		Audio*8	yes (ch1)	-
PTZ		yes	-	
Direct connection to camera	RTP over HTTP	-	-	
	WV-ASC970 (Ver14.00)	MJPEG	yes	yes
		MPEG4	yes	-
		H.264	yes	yes
		Audio*8	yes (ch1)	-
PTZ		yes	yes	
Direct connection to camera	RTP over HTTP	yes	yes	
	WJ-GXD400 (Ver2.21)	MJPEG	yes	yes
		MPEG4	yes	-
		H.264	yes	yes
		Audio*9	yes (ch1)	-
PTZ		-	-	
Direct connection to camera	RTP over HTTP	yes	yes	
	BB-HNP17 (Ver4.05)	MJPEG	yes	yes
		MPEG4	yes	-
		H.264	yes	yes
		Audio*8	yes (ch1)	-
PTZ		yes	yes	
Direct connection to camera	RTP over HTTP	yes	yes	

*1 : Only for remote PTZ cameras.

*5 : WV-ASM100 does not support displaying 16:9.

*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA.

*7 : Support functions are different depending on the "Image capture mode". For details on "Image capture mode", please refer to the operating instructions.

*8 : Supported G.726.

*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.

*14 : Streams of H.264(3) and H.264(4) are not supported.

	Function	WJ-NV300	WJ-NV200	WJ-ND400K	WJ-ND300	WJ-ND200	WJ-HD616/HD716	WW-SFN531/SFR531/SFV531
WV-ASM200 (V4.00) Via Recorder	MJPEG	yes	yes	yes	yes	yes	-	-
	MPEG4	-	yes	yes	yes	yes	-	-
	H.264	yes	yes	yes	yes	yes	yes	-
	Original	-	-	-	-	-	-	yes
	Audio*8	Live/Playback(Receive)	Live/Playback (Recieve)	Live/Playback (Recieve)	-	Playback (Recieve)	Live/Playback (Recieve)	-
	PTZ	yes	yes	yes	yes	yes	yes	yes
	VMD	yes	yes	yes	-	-	yes	-
	RTP over HTTP	yes	yes	yes	-	-	yes	-
WV-ASM100 (Ver8.00) Via Recorder	MJPEG	-	yes	yes	yes	yes	-	-
	MPEG4	-	yes	yes	yes	yes	-	-
	H.264	-	yes	yes	yes	yes	yes	-
	Original	-	-	-	-	-	-	yes
	Audio*8	-	Live/Playback (Recieve)	Live/Playback (Recieve)	-	Playback (Recieve)	Live/Playback (Recieve)	-
	PTZ	-	yes	yes	yes	yes	yes	yes
	VMD	-	yes	yes	-	-	yes	-
	RTP over HTTP	-	yes	yes	-	-	yes	-
WV-ASM970 (Ver14.00)	MJPEG	yes	yes	yes	yes (Playback only)	yes (Playback only)	-	-
	MPEG4	-	yes	yes	yes (Playback only)	yes (Playback only)	-	-
	H.264	yes	yes	yes	yes (Playback only)	yes (Playback only)	yes	-
	Original	-	-	-	-	-	-	yes
	Audio*8	Live/Playback (Receive)	Playback (Recieve)	Playback (Recieve)	-	Playback (Recieve)	Playback (Recieve)	-
	PTZ	yes	yes	yes	-	-	yes	yes
	VMD	yes	yes	yes	-	-	yes	-
	RTP over HTTP	yes	yes	yes	-	-	yes	-
WJ-GXD400 (Ver2.21) *6	MJPEG	-	-	yes	yes (Playback only)	yes (Playback only)	-	-
	MPEG4	-	-	yes	yes (Playback only)	yes (Playback only)	-	-
	H.264	-	-	yes	yes (Playback only)	yes (Playback only)	yes	-
	Original	-	-	-	-	-	-	yes
	Audio*9	-	-	Playback (Recieve)	-	Playback (Recieve)	Playback (Recieve)	-
	PTZ	-	-	yes	-	-	yes	yes
	VMD	-	-	yes	-	-	yes	-
	RTP over HTTP	-	-	-	-	-	-	-

*6 : Supported resolutions of WJ-GXD400 are only 1280x960, VGA and QVGA.

*8 : Supported only G.726.

*9 : Supported G.726 as an Audio and MPEG4/H.264 as a Video.